



## MATERIAL FACT SHEET

### 409259 FR-A840-00052-E2-60CRN

#### General Data

|                     |                                        |
|---------------------|----------------------------------------|
| Product Hierarchy   | IAK24101                               |
|                     | INVERTER                               |
|                     | FR-A840 from 00023 to 00620            |
| Ext. Material Group | 10 STANDARD ITEM                       |
| ABC Indicator       | C (Non-Stock Material / Make-to-Order) |

e-shop: [https://mitsubishi-electric-eshop.mee.com/mee/FA\\_IA/EUR/en/p/000000000000409259](https://mitsubishi-electric-eshop.mee.com/mee/FA_IA/EUR/en/p/000000000000409259)

#### Product Components

|                                              |               |
|----------------------------------------------|---------------|
| <a href="#">297568 / FR-A840-00052-E2-60</a> | 1 pc required |
|----------------------------------------------|---------------|

#### FA-Inverter: Inverter

|                              |                                |
|------------------------------|--------------------------------|
| Series                       | FR-A800 PLUS SERIES            |
| Type                         | FR-A800-CRN (FOR CRANES)       |
| Minimum Rated Voltage (V)    | 380                            |
| Min. Permissible Voltage (V) | 323                            |
| Maximum Rated Voltage (V)    | 500                            |
| Max. Permissible Voltage (V) | 550                            |
| Current Type                 | AC                             |
| Phases                       | 3                              |
| Rated Output Current SLD (A) | 5,2                            |
| Rated Output Current LD (A)  | 4,8                            |
| Rated Output Current ND (A)  | 4                              |
| Rated Output Current HD (A)  | 2,5                            |
| Rated Motor Capacity ND (kW) | 1,5                            |
| Rated Motor Capacity HD (kW) | 0,75                           |
| Frequency Range (Hz)         | 0,2-590                        |
| Control Method               | MAGNETIC FLUX VECTOR CONTROL   |
| Control Method (2)           | PM SENSORLESS VECTOR CONTROL   |
| Control Method (3)           | REAL SENSORLESS VECTOR CONTROL |
| Control Method (4)           | SOFT-PWM/HIGH FREQUENCY PWM    |
| Control Method (5)           | V/F CONTROL                    |
| Control Method (6)           | VECTOR CONTROL (WITH FR-A8AP)  |
| Motor Type                   | INDUCTION MOTOR, PM MOTOR      |
| Brake Chopper ED (%)         | -                              |
| Integrated EMC Filter        | YES                            |
| Safe Torque Off (STO)        | YES                            |
| Regenerative (4Q)            | NO                             |
| Integrated DC Choke          | NO                             |
| Display                      | FR-DU08                        |
| Display Type                 | 5 DIGITS LED (12 SEGMENT)      |
| PLC Function                 | YES                            |
| Program Memory               | 6K                             |
| Program Memory Unit          | STEPS                          |
| Integrated Digital Inputs    | 12                             |
| Digital Outputs (Transistor) | 5                              |
| Digital Outputs (Relay)      | 2                              |
| Integrated Analogue Inputs   | 3                              |
| Integrated Analogue Outputs  | 2                              |
| IO Type of Terminal Block    | SPRING CLAMP                   |
| Expandable                   | YES                            |
| USB                          | 1+1 MINI                       |
| Ethernet Port                | 1                              |
| Built-In Network             | CC-LINK IE FIELD NETWORK       |
| Built-In Network (2)         | CC-LINK IE FIELD NETWORK BASIC |
| Built-In Network (3)         | MODBUS/TCP                     |
| Leakage Current (mA)         | 35(DELTA) / 2(STAR)            |

|                               |      |
|-------------------------------|------|
| Power Loss SLD (W)            | 85   |
| Power Loss LD (W)             | 80   |
| Power Loss ND (W)             | 70   |
| Power Loss HD (W)             | 50   |
| Standby Power Consumption (W) | 19   |
| Protection Class              | IP20 |

#### Product Dimensions & Weight

|             |     |
|-------------|-----|
| Width (mm)  | 150 |
| Height (mm) | 260 |
| Depth (mm)  | 140 |
| Weight (kg) | 3,3 |

#### Logistic Dimensions & Gross Weight

|                   |        |
|-------------------|--------|
| Length (cm)       | 35,0   |
| Width (cm)        | 21,0   |
| Height (cm)       | 17,5   |
| Gross Weight (kg) | 3,750  |
| Volume (cdm)      | 12,863 |

#### Stock Data

|                              |     |
|------------------------------|-----|
| Planned Delivery Time (Days) | 184 |
|------------------------------|-----|

#### Life Cycle

|             |                |
|-------------|----------------|
| Sales Start | 01.12.2018     |
| Predecessor | No Predecessor |

#### Additional Product Information

|                            |                  |
|----------------------------|------------------|
| Difference to Standard 1   | CRANE CONTROL    |
| Binding Tariff Information | DEBTI-21865/22-1 |
| BTI validity date          | 01.01.2026       |
| Battery included           | NO               |

#### Export Data

|                                          |            |
|------------------------------------------|------------|
| Legal Control (Dual Use List)            | Not Listed |
| Country of Origin                        | China (CN) |
| Preference Status (Supplier Declaration) | Non EU     |

#### Environmental

|                            |           |
|----------------------------|-----------|
| Dangerous Goods Class      | NO        |
| Dangerous Goods Identifier | NO        |
| RoHS Compliance            | COMPLIANT |
| WEEE                       | B2B       |

#### Conformity

|                    |                     |
|--------------------|---------------------|
| CE                 | COMPLIANT           |
| UL/cUL             | COMPLIANT           |
| EAC                | COMPLIANT           |
| Shipping Approvals | ABS,BV,DNV GL,LR,NK |
| UKCA               | COMPLIANT           |

#### Documentation & Media Data

|                                |                                                                                                                                                                                                                                                                                                                 |
|--------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Manual URL Indicator           | <a href="https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=bltdae25c2bd5f2ff94&amp;q=FR-A840-00052-E2-60CRN&amp;doc-lang=en">https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=bltdae25c2bd5f2ff94&amp;q=FR-A840-00052-E2-60CRN&amp;doc-lang=en</a> |
| Certificates URL Indicator     | <a href="https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=blt8050dd1408c11cc2&amp;q=FR-A840-00052-E2-60CRN&amp;doc-lang=en">https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=blt8050dd1408c11cc2&amp;q=FR-A840-00052-E2-60CRN&amp;doc-lang=en</a> |
| CAD URL Indicator              | <a href="https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=blt26ecc97a31a841c1&amp;q=FR-A840-00052-E2-60CRN&amp;doc-lang=en">https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=blt26ecc97a31a841c1&amp;q=FR-A840-00052-E2-60CRN&amp;doc-lang=en</a> |
| Network configuration file URL | <a href="https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=blte8cf990c7c524b4e&amp;q=FR-A840-00052-E2-60CRN&amp;doc-lang=en">https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=blte8cf990c7c524b4e&amp;q=FR-A840-00052-E2-60CRN&amp;doc-lang=en</a> |

#### Product Packaging

|                   |     |
|-------------------|-----|
| Cardboard (g)     | 800 |
| Other paper (g)   | 0   |
| Aluminum (g)      | 0   |
| Steel (g)         | 0   |
| Styrofoam (g)     | 0   |
| Other plastic (g) | 10  |
| Wood (g)          | 0   |

|            |   |
|------------|---|
| Glass (g)  | 0 |
| Others (g) | 0 |

#### Spare parts

| Material               | Description                              | Quantity | Unit |
|------------------------|------------------------------------------|----------|------|
| 591486                 | FR-A870 COVER INTERFACE ALL              | 1        | PC   |
| <a href="#">283660</a> | FR-A840-00023-00126-2-60 COVER LOWER FR. | 1        | PC   |
| <a href="#">283661</a> | FR-A840-00023-00126-2-60 COVER WIRING    | 1        | PC   |
| 591494                 | FR-A870 GROUND WIRE ETH ALL              | 1        | PC   |

#### Compatible products

| Material               | Description / Price List Text / Classification                                                                                                 |
|------------------------|------------------------------------------------------------------------------------------------------------------------------------------------|
| <a href="#">46603</a>  | FR-ABR-H1.5K<br>External High-Duty Brake Resistor; 400V; 1,5kW; 350 Ohm; 10%ED<br>Class 100100407: FA-Inverter: Brake Option                   |
| <a href="#">70727</a>  | FR-A5 CBL 1<br>Cable for connecting Inverter and Programming panel; 1m<br>Class 100100405: FA-Inverter: Cable                                  |
| <a href="#">70728</a>  | FR-A5 CBL 2,5<br>Cable for connecting Inverter and Programming panel; 2,5m<br>Class 100100405: FA-Inverter: Cable                              |
| <a href="#">70729</a>  | FR-A5 CBL 5<br>Cable for connecting Inverter and Programming panel; 5m<br>Class 100100405: FA-Inverter: Cable                                  |
| <a href="#">87244</a>  | FR-BAL-B-4,0K<br>Input Reactor 3ph; 400V; for 4,0kW<br>Class 100100406: FA-Inverter: Choke                                                     |
| <a href="#">127947</a> | BU-UFS 22<br>Brake Unit 400V; Contin. Braking Current 22A; 10sec peak current 34A<br>Class 100100407: FA-Inverter: Brake Option                |
| <a href="#">127948</a> | BU-UFS 40<br>Brake Unit 400V; Contin. Braking Current 34A; 10sec peak current 55A<br>Class 100100407: FA-Inverter: Brake Option                |
| <a href="#">127950</a> | BU-UFS 110<br>Brake Unit 400V; Contin. Braking Current 44A; 10sec peak current 138A<br>Class 100100407: FA-Inverter: Brake Option              |
| <a href="#">129629</a> | RUFC22 (PACK OF 1)<br>Brake Resistor for BU-UFS22; 2kW; 1x24 Ohm<br>Class 100100407: FA-Inverter: Brake Option                                 |
| <a href="#">129630</a> | RUFC40 (PACK OF 2)<br>Brake Resistor Set for BU-UFS40; 2kW; 2x6,8 Ohm<br>Class 100100407: FA-Inverter: Brake Option                            |
| <a href="#">129631</a> | RUFC110 (PACK OF 4)<br>Break Resistor Set for BU-UFS110; 2kW; 4x6,8 Ohm<br>Class 100100407: FA-Inverter: Brake Option                          |
| <a href="#">167612</a> | FR-RJ45-HUB10<br>Distribution Module for RJ45; 10 way<br>Class 100100403: FA-Inverter: External Option                                         |
| <a href="#">167613</a> | FR-RJ45-HUB4<br>Distribution Module for RJ45; 4 way<br>Class 100100403: FA-Inverter: External Option                                           |
| <a href="#">167614</a> | FR-RJ45-TR<br>Terminal Resistor Plug RJ45<br>Class 100100403: FA-Inverter: External Option                                                     |
| <a href="#">193677</a> | FFR-BS-00126-18A-SF100<br>Radio Noise Filter for FR-A&F-00023-00126; C1 20m; C2 100m<br>Class 100100404: FA-Inverter: Filter                   |
| <a href="#">209735</a> | FFR-SI-4.5A-SS1<br>Sinusfilter for 200/230/400V Inverters; max. 4,5A; FT=4-16kHz; (W*H*D) 125*180*75mm<br>Class 100100404: FA-Inverter: Filter |
| <a href="#">209755</a> | FFR-DT-10A-SS1<br>du/dt Filter for 400V Inverters; max. 10A; FT=2-16kHz; (W*H*D) 100*120*65mm<br>Class 100100404: FA-Inverter: Filter          |
| <a href="#">221540</a> | USB-CAB-5M<br>USB 2.0 connection cabel, plug USB A to plug USB B (mini), 5m<br>Class 100100303: FA-HMI: Cable                                  |
| <a href="#">238344</a> | FFR-HEL-H1.5K-E<br>DC Link choke for 400V Inverter; 1,5kW; 20,5mH; 3,1A<br>Class 100100406: FA-Inverter: Choke                                 |

| Material               | Description / Price List Text / Classification                                                                                                                     |
|------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <a href="#">247642</a> | BH-D6 3P 10A TYPE C N<br>MCB 3-poles, Rated current 10A, Operating characteristic C<br>Class 100100801: FA-MCB: Miniature Circuit Breaker                          |
| <a href="#">247889</a> | BH-D10 3P 10A TYPE C N<br>Miniature circuit breaker 10 A, 3 pole, Type C<br>Class 100100801: FA-MCB: Miniature Circuit Breaker                                     |
| <a href="#">254684</a> | NF32-SV 3P 10A<br>Circuit breaker 3pole. In = 10A; Icu = Ics = 2,5kA at AC 440V<br>Class 100100901: FA-MCCB: Moulded-Case Circuit Breaker                          |
| <a href="#">254743</a> | NF63-SV 3P 10A<br>Circuit breaker 3pole. In = 10A; Icu = Ics = 7,5kA at AC 440V<br>Class 100100901: FA-MCCB: Moulded-Case Circuit Breaker                          |
| <a href="#">254778</a> | NF63-HV 3P 10A<br>Circuit breaker 3pole. In = 10A; Icu / Ics = 10 / 8kA at AC 440V<br>Class 100100901: FA-MCCB: Moulded-Case Circuit Breaker                       |
| <a href="#">262948</a> | A8NDPV1<br>Profibus DPV1 with Dsub Interface for FR-A/F800<br>Class 100100402: FA-Inverter: Internal Option                                                        |
| <a href="#">262949</a> | A8NPRT_2P<br>Profinet 2port Interface for FR-A/F800 with Drive Profile<br>Class 100100402: FA-Inverter: Internal Option                                            |
| <a href="#">262950</a> | A8NEIP_2P<br>EtherNet/IP 2port Interface for FR-A/F800<br>Class 100100402: FA-Inverter: Internal Option                                                            |
| <a href="#">269426</a> | FR-A8AX<br>16-Bit-Digital-Input; BCD/Binary-Code; 24V DC; 5mA for FR-F/A800<br>Class 100100402: FA-Inverter: Internal Option                                       |
| <a href="#">269427</a> | FR-A8AY<br>Digital-/Analog Output; Output load: 24V DC; 0,1A for FR-F/A800<br>Class 100100402: FA-Inverter: Internal Option                                        |
| <a href="#">269428</a> | FR-A8AR<br>Relay output; 3 additional output relays for FR-A/F800<br>Class 100100402: FA-Inverter: Internal Option                                                 |
| <a href="#">269429</a> | FR-A8AP<br>Incremental Encoder Feedback for FR-A800<br>Class 100100402: FA-Inverter: Internal Option                                                               |
| <a href="#">269430</a> | FR-A8AL<br>Incremental encoder feedback terminal block for FR-A800<br>Class 100100402: FA-Inverter: Internal Option                                                |
| <a href="#">269431</a> | FR-A8NC<br>CC-Link Interface for FR-A/F800<br>Class 100100402: FA-Inverter: Internal Option                                                                        |
| <a href="#">269432</a> | FR-A8ND<br>DeviceNet Interface for FR-A/F800<br>Class 100100402: FA-Inverter: Internal Option                                                                      |
| <a href="#">273102</a> | FR-A8NCE<br>CC-Link IE Field Interface for FR-A/F800<br>Class 100100402: FA-Inverter: Internal Option                                                              |
| <a href="#">274514</a> | FR-A8NP<br>ProfibusDP Interface for FR-A/F800 with FR-A/F700 PPO types<br>Class 100100402: FA-Inverter: Internal Option                                            |
| <a href="#">274525</a> | FR-LU08<br>Clear text LCD Parameter unit for all units of 800 Series<br>Class 100100403: FA-Inverter: External Option                                              |
| <a href="#">274526</a> | FR-A8TAT<br>Adapter for control terminal of A/F700 to A/F800<br>Class 100100402: FA-Inverter: Internal Option                                                      |
| <a href="#">275503</a> | FR Configurator-M+FR-Configurator2<br>FR-Configurator for 700 series; multi I + FR-Configurator2 for 800 series<br>Class 100101203: FA-Software: Software Inverter |
| <a href="#">277880</a> | FR-A8CN01<br>Heatsink Protrusion Attachment for FR-F/A840 to 00126; for FR-A820-00105/00250<br>Class 100100403: FA-Inverter: External Option                       |
| <a href="#">279140</a> | S-T10 AC24V 1A<br>Magnetic contactor. 4kW; 1NO; Us = AC 24V, 50Hz<br>Class 100101001: FA-MC: Magnetic Contactor                                                    |
| <a href="#">279141</a> | S-T10 AC48V 1A<br>Magnetic contactor. 4kW; 1NO; Us = AC 48V, 50Hz<br>Class 100101001: FA-MC: Magnetic Contactor                                                    |

| Material               | Description / Price List Text / Classification                                                                                               |
|------------------------|----------------------------------------------------------------------------------------------------------------------------------------------|
| <a href="#">279142</a> | S-T10 AC100V 1A<br>Magnetic contactor. 4kW; 1NO; Us = AC 100V, 50Hz<br>Class 100101001: FA-MC: Magnetic Contactor                            |
| <a href="#">279143</a> | S-T10 AC200V 1A<br>Magnetic contactor. 4kW; 1NO; Us = AC 200V, 50Hz<br>Class 100101001: FA-MC: Magnetic Contactor                            |
| <a href="#">279144</a> | S-T10 AC300V 1A<br>Magnetic contactor. 4kW; 1NO; Us = AC 300V, 50Hz<br>Class 100101001: FA-MC: Magnetic Contactor                            |
| <a href="#">279195</a> | S-T10 AC400V 1A<br>Magnetic contactor. 4kW; 1NO; Us = AC 400V, 50Hz<br>Class 100101001: FA-MC: Magnetic Contactor                            |
| <a href="#">279196</a> | S-T10 AC500V 1A<br>Magnetic contactor. 4kW; 1NO; Us = AC 500V, 50Hz<br>Class 100101001: FA-MC: Magnetic Contactor                            |
| <a href="#">279197</a> | S-T10 AC24V 1B<br>Magnetic contactor. 4kW; 1NC; Us = AC 24V, 50Hz<br>Class 100101001: FA-MC: Magnetic Contactor                              |
| <a href="#">279198</a> | S-T10 AC48V 1B<br>Magnetic contactor. 4kW; 1NC; Us = AC 48V, 50Hz<br>Class 100101001: FA-MC: Magnetic Contactor                              |
| <a href="#">279199</a> | S-T10 AC100V 1B<br>Magnetic contactor. 4kW; 1NC; Us = AC 100V, 50Hz<br>Class 100101001: FA-MC: Magnetic Contactor                            |
| <a href="#">279200</a> | S-T10 AC200V 1B<br>Magnetic contactor. 4kW; 1NC; Us = AC 200V, 50Hz<br>Class 100101001: FA-MC: Magnetic Contactor                            |
| <a href="#">279201</a> | S-T10 AC300V 1B<br>Magnetic contactor. 4kW; 1NC; Us = AC 300V, 50Hz<br>Class 100101001: FA-MC: Magnetic Contactor                            |
| <a href="#">279202</a> | S-T10 AC400V 1B<br>Magnetic contactor. 4kW; 1NC; Us = AC 400V, 50Hz<br>Class 100101001: FA-MC: Magnetic Contactor                            |
| <a href="#">279203</a> | S-T10 AC500V 1B<br>Magnetic contactor. 4kW; 1NC; Us = AC 500V, 50Hz<br>Class 100101001: FA-MC: Magnetic Contactor                            |
| <a href="#">283939</a> | FR-A8APR<br>Resolver interface/orientation control/Resolver feedback control/vector control<br>Class 100100402: FA-Inverter: Internal Option |
| <a href="#">283940</a> | FR-A8AZ<br>Analog Input/ output, Thermistor interface<br>Class 100100402: FA-Inverter: Internal Option                                       |
| <a href="#">284809</a> | A8NECT_2P<br>Ethercat 2port Interface for FR-A/F800<br>Class 100100402: FA-Inverter: Internal Option                                         |
| <a href="#">285244</a> | FR-A8TP<br>Incremental Encoder Feedback Terminal Block for FR-A800<br>Class 100100402: FA-Inverter: Internal Option                          |
| <a href="#">289335</a> | FR-A8NS<br>SSCNet Interface for FR-A800<br>Class 100100402: FA-Inverter: Internal Option                                                     |
| <a href="#">291918</a> | BHW-T10 3P Type B 10A<br>MCB 3-pole, Rated current 10A, Operating characteristic B<br>Class 100100801: FA-MCB: Miniature Circuit Breaker     |
| <a href="#">291990</a> | BHW-T10 3P Type C 10A<br>MCB 3-pole, Rated current 10A, Operating characteristic C<br>Class 100100801: FA-MCB: Miniature Circuit Breaker     |
| <a href="#">292080</a> | BHW-T10 3P Type D 10A<br>MCB 3-pole, Rated current 10A, Operating characteristic D<br>Class 100100801: FA-MCB: Miniature Circuit Breaker     |
| <a href="#">294939</a> | FR-D-Sub9-A8NP-01<br>D-Sub9 Connection Adapter for FR-A8NP + Cover<br>Class 100100402: FA-Inverter: Internal Option                          |
| <a href="#">296613</a> | FR-LU08-01<br>Clear text LCD Parameter unit for all units of 800 Series (IP55)<br>Class 100100403: FA-Inverter: External Option              |
| <a href="#">297422</a> | FR-A8APS<br>Absolute Encoder Feedback for FR-A800 (EnDat)<br>Class 100100402: FA-Inverter: Internal Option                                   |

| Material               | Description / Price List Text / Classification                                                                                                     |
|------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------|
| <a href="#">298153</a> | FR-A8NCA<br>CANopen Interface for FR-A800<br>Class 100100402: FA-Inverter: Internal Option                                                         |
| <a href="#">307170</a> | FR-A8ERS-60<br>Optioncard to change Ethernet board to serial communication<br>Class 100100402: FA-Inverter: Internal Option                        |
| <a href="#">307170</a> | FR-A8ERS-60<br>Optioncard to change Ethernet board to serial communication<br>Class 100100402: FA-Inverter: Internal Option                        |
| <a href="#">403614</a> | FR-A8APA<br>SinCos Encoder Feedback for FR-A800<br>Class 100100402: FA-Inverter: Internal Option                                                   |
| <a href="#">591572</a> | RHF-5P 5.5-400-50-20-C<br>High efficient double-stage passive harmonic filter for THDi <5%;400V;50Hz;5.5kW<br>Class 100100404: FA-Inverter: Filter |
| <a href="#">591592</a> | RHF-8P 5.5-400-50-20-C<br>High efficient double-stage passive harmonic filter for THDi <8%;400V;50Hz;5.5kW<br>Class 100100404: FA-Inverter: Filter |