



## MATERIAL FACT SHEET

### 307221 FR-F840-00620-E2-60

#### General Data

|                     |                             |
|---------------------|-----------------------------|
| Product Hierarchy   | IAK24201                    |
|                     | INVERTER                    |
|                     | FR-F840 from 00023 to 00620 |
| Ext. Material Group | 10 STANDARD ITEM            |
| ABC Indicator       | A (Available from Stock)    |

e-shop: <https://emea-fa.mitsubishielectric.com/fa/shop/material-page/00000000000307221>

#### FA-Inverter: Inverter

|                               |                                |
|-------------------------------|--------------------------------|
| Series                        | FR-F800 SERIES                 |
| Type                          | FR-F800-E INVERTER             |
| Minimum Rated Voltage (V)     | 380                            |
| Min. Permissible Voltage (V)  | 323                            |
| Maximum Rated Voltage (V)     | 500                            |
| Max. Permissible Voltage (V)  | 550                            |
| Current Type                  | AC                             |
| Phases                        | 3                              |
| Rated Output Current SLD (A)  | 62                             |
| Rated Output Current LD (A)   | 57                             |
| Rated Motor Capacity SLD (kW) | 30                             |
| Rated Motor Capacity LD (kW)  | 30                             |
| Frequency Range (Hz)          | 0,2–590                        |
| Control Method                | MAGNETIC FLUX VECTOR CONTROL   |
| Control Method (2)            | PM SENSORLESS VECTOR CONTROL   |
| Control Method (3)            | SOFT-PWM/HIGH FREQUENCY PWM    |
| Control Method (4)            | V/F CONTROL                    |
| Motor Type                    | INDUCTION MOTOR, PM MOTOR      |
| Integrated EMC Filter         | YES                            |
| Safe Torque Off (STO)         | YES                            |
| Regenerative (4Q)             | NO                             |
| Integrated DC Choke           | NO                             |
| Display                       | FR-DU08                        |
| Display Type                  | 5 DIGITS LED (12 SEGMENT)      |
| PLC Function                  | YES                            |
| Program Memory                | 6K                             |
| Program Memory Unit           | STEPS                          |
| Integrated Digital Inputs     | 12                             |
| Digital Outputs (Transistor)  | 5                              |
| Digital Outputs (Relay)       | 2                              |
| Integrated Analogue Inputs    | 3                              |
| Integrated Analogue Outputs   | 2                              |
| IO Type of Terminal Block     | SPRING CLAMP                   |
| Expandable                    | YES                            |
| USB                           | 1+1 MINI                       |
| Ethernet Port                 | 1                              |
| Built-In Network              | BACNET/IP                      |
| Built-In Network (2)          | CC-LINK IE FIELD NETWORK BASIC |
| Built-In Network (3)          | MELSOFT/FA                     |
| Built-In Network (4)          | MODBUS/TCP                     |
| Built-In Network (5)          | SLMP                           |
| Built-In Network (6)          | iQSS                           |
| Leakage Current (mA)          | 35(Delta) / 2(Star)            |
| Power Loss SLD (W)            | 740                            |
| Power Loss LD (W)             | 675                            |
| Standby Power Consumption (W) | 20                             |
| Protection Class              | IP20                           |

**Product Dimensions & Weight**

|             |     |
|-------------|-----|
| Width (mm)  | 250 |
| Height (mm) | 400 |
| Depth (mm)  | 190 |
| Weight (kg) | 15  |

**Logistic Dimensions & Gross Weight**

|                   |        |
|-------------------|--------|
| Length (cm)       | 56,0   |
| Width (cm)        | 40,0   |
| Height (cm)       | 36,0   |
| Gross Weight (kg) | 16,872 |
| Volume (cdm)      | 80,640 |

**Stock Data**

|                              |     |
|------------------------------|-----|
| Planned Delivery Time (Days) | 119 |
|------------------------------|-----|

**Life Cycle**

|             |                           |
|-------------|---------------------------|
| Sales Start | 15.02.2017                |
| Predecessor | 156599 / FR-F740-00620-EC |

**Additional Product Information**

|                            |                  |
|----------------------------|------------------|
| Binding Tariff Information | DEBTI-21865/22-1 |
| BTI validity date          | 01.01.2026       |
| Battery included           | NO               |
| Product Code               | INV(O/O MDI)     |

**Export Data**

|  |            |
|--|------------|
| Commodity Code                           | 85371091   |
| Legal Control (Dual Use List)            | Not Listed |
| Country of Origin                        | China (CN) |
| Preference Status (Supplier Declaration) | Non EU     |

**Environmental**

|                            |           |
|----------------------------|-----------|
| REACH Limit Exceeded       | NO        |
| Dangerous Goods Class      | NO        |
| Dangerous Goods Identifier | NO        |
| RoHS Compliance            | COMPLIANT |
| WEEE                       | B2B       |

**Conformity**

|                    |               |
|--------------------|---------------|
| CE                 | COMPLIANT     |
| UL/cUL             | COMPLIANT     |
| EAC                | NON-COMPLIANT |
| Shipping Approvals | DNV,ABS       |
| UKCA               | COMPLIANT     |

**Documentation & Media Data**

|                                |   |
|--------------------------------|---|
| Manual URL Indicator           | <a href="https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=bltdae25c2bd5f2ff94&amp;q=FR-F840-00620-E2-60&amp;doc-lang=en">https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=bltdae25c2bd5f2ff94&amp;q=FR-F840-00620-E2-60&amp;doc-lang=en</a> |
| Certificates URL Indicator     | <a href="https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=blt8050dd1408c11cc2&amp;q=FR-F840-00620-E2-60&amp;doc-lang=en">https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=blt8050dd1408c11cc2&amp;q=FR-F840-00620-E2-60&amp;doc-lang=en</a> |
| CAD URL Indicator              | <a href="https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=blt26ecc97a31a841c1&amp;q=FR-F840-00620-E2-60&amp;doc-lang=en">https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=blt26ecc97a31a841c1&amp;q=FR-F840-00620-E2-60&amp;doc-lang=en</a> |
| Network configuration file URL | <a href="https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=blte8cf990c7c524b4e&amp;q=FR-F840-00620-E2-60&amp;doc-lang=en">https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=blte8cf990c7c524b4e&amp;q=FR-F840-00620-E2-60&amp;doc-lang=en</a> |

**Product Packaging**

|                   |        |
|-------------------|--------|
| Cardboard (g)     | 1855   |
| Other paper (g)   | 0      |
| Aluminum (g)      | 0      |
| Steel (g)         | 0      |
| Styrofoam (g)     | 482    |
| Other plastic (g) | 14,476 |
| Wood (g)          | 0      |
| Glass (g)         | 0      |
| Others (g)        | 0      |

**Spare parts**

| Material | Description | Quantity | Unit |
|----------|-------------|----------|------|
|----------|-------------|----------|------|

| Material               | Description                              | Quantity | Unit |
|------------------------|--|----------|------|
| <a href="#">282886</a> | FR-A840-00470-00620-2-60 PCB MA          | 1        | PC   |
| <a href="#">282896</a> | FR-A840-00470-00770-2-60 PCB GA          | 1        | PC   |
| <a href="#">282904</a> | FR-A840-00470-00620-2-60 PCB AUX         | 1        | PC   |
| <a href="#">307205</a> | FR-CF80-01-E2-60                         | 1        | PC   |
| <a href="#">282932</a> | FR-A840/842/846-ALL TERMINAL BLOCK A80TA | 1        | PC   |
| <a href="#">283438</a> | FR-A840-00470-00770-2-60 THYRISTORMODULE | 1        | PC   |
| <a href="#">283450</a> | FR-A840-00470-01800-2-60 FAN             | 2        | PC   |
| <a href="#">283460</a> | FR-A840-00470-00620-2-60 INRUSH RES.     | 1        | PC   |
| <a href="#">283467</a> | FR-A840-00620-2-60 DCCT Current transf.  | 1        | PC   |
| <a href="#">283483</a> | FR-A840-00470-00620-2-60 CBL MA-CPU      | 1        | PC   |
| <a href="#">283587</a> | FR-A840-00620-2-60 CAPACITOR             | 4        | PC   |
| <a href="#">283694</a> | FR-A840-00470/00620-2-60 CHASSIS         | 1        | PC   |
| <a href="#">283695</a> | FR-A840-00470/00620-2-60 CASE            | 1        | PC   |
| <a href="#">283696</a> | FR-A840-00470/00620-2-60 COVER UPPER FR. | 1        | PC   |
| <a href="#">283697</a> | FR-A840-00470/00620-2-60 COVER LOWER FR. | 1        | PC   |
| <a href="#">283698</a> | FR-A840-00470/00620-2-60 COVER WIRING    | 1        | PC   |
| <a href="#">283699</a> | FR-A840-00470/00620-2-60 COVER FAN       | 1        | PC   |
| <a href="#">734507</a> | FR-A840-00470/00620-2-60 COVER TERMINAL  | 1        | PC   |
| <a href="#">748953</a> | FR-F840-00620-E2-60 THYRISTOR SKKH172/16 | 1        | PC   |

### Compatible products

| Material               | Description / Price List Text / Classification  |
|------------------------|---|
| <a href="#">70727</a>  | FR-A5 CBL 1<br>Cable for connecting Inverter and Programming panel; 1m<br>Class 100100405: FA-Inverter: Cable                               |
| <a href="#">70728</a>  | FR-A5 CBL 3<br>Cable for connecting Inverter and Programming panel; 3m<br>Class 100100405: FA-Inverter: Cable                               |
| <a href="#">70729</a>  | FR-A5 CBL 5<br>Cable for connecting Inverter and Programming panel; 5m<br>Class 100100405: FA-Inverter: Cable                               |
| <a href="#">87248</a>  | FR-BAL-B-30K<br>Input Reactor 3ph; 400V; for 30kW<br>Class 100100406: FA-Inverter: Choke  |
| <a href="#">88426</a>  | SC-FR-PC CONNECTION CABLE PC>INVERTER<br>Programming Cable RS 232>RS485/422; 5m<br>Class 100100405: FA-Inverter: Cable                      |
| <a href="#">127950</a> | BU-UFS 110<br>Brake Unit 400V; Contin. Braking Current 44A; 10sec peak current 138A<br>Class 100100407: FA-Inverter: Brake Option           |
| <a href="#">157515</a> | FR-ADP<br>Adaptor Module for Operator Panel FR-DU07<br>Class 100100403: FA-Inverter: External Option  |
| <a href="#">167612</a> | FR-RJ45-HUB10<br>Distribution Module for RJ45; 10 way<br>Class 100100403: FA-Inverter: External Option                                      |
| <a href="#">167613</a> | FR-RJ45-HUB4<br>Distribution Module for RJ45; 4 way<br>Class 100100403: FA-Inverter: External Option  |
| <a href="#">167614</a> | FR-RJ45-TR<br>Terminal Resistor Plug RJ45<br>Class 100100403: FA-Inverter: External Option  |
| <a href="#">193680</a> | FFR-BS-00620-75A-SF100<br>Radio Noise Filter for FR-A&F-00470-00620; C1 20m; C2 100m<br>Class 100100404: FA-Inverter: Filter                |
| <a href="#">209741</a> | FFR-SI-62A-SS1<br>Sinusfilter for 200/400V Inverters; max. 62A; FT=4-16kHz; (W*H*D) 240*290*220mm<br>Class 100100404: FA-Inverter: Filter   |
| <a href="#">209758</a> | FFR-DT-93A-SS1<br>du/dt Filter for 400V Inverters; max. 93A; FT=2-16kHz; (W*H*D) 190*240*100mm<br>Class 100100404: FA-Inverter: Filter      |
| <a href="#">221540</a> | USB-CAB-5M<br>USB 2.0 connection cabel, plug USB A to plug USB B (mini), 5m<br>Class 100100303: FA-HMI: Cable                               |
| <a href="#">238368</a> | FFR-HEL-30K-E<br>DC Link choke for 200V Inverter; 30kW; 0,23mH; 129A<br>Class 100100406: FA-Inverter: Choke                                 |
| <a href="#">254842</a> | NF125-SV 3P 100A<br>Circuit breaker 3pole. In = 100A; Icu = Ics = 25kA at AC 440V<br>Class 100100901: FA-MCCB: Moulded-Case Circuit Breaker |

| Material               | Description / Price List Text / Classification   |
|------------------------|--|
| <a href="#">254843</a> | NF125-SV 3P 125A<br>Circuit breaker 3pole. In = 125A; Icu = Ics = 25kA at AC 440V<br>Class 100100901: FA-MCCB: Moulded-Case Circuit Breaker                        |
| <a href="#">262948</a> | A8NDPV1<br>Profibus DPV1 with Dsub Interface for FR-A/F800<br>Class 100100402: FA-Inverter: Internal Option  |
| <a href="#">262949</a> | A8NPRT_2P<br>Profinet 2port Interface for FR-A/F800 with Drive Profile<br>Class 100100402: FA-Inverter: Internal Option  |
| <a href="#">262950</a> | A8NEIP_2P<br>EtherNet/IP 2port Interface for FR-A/F800<br>Class 100100402: FA-Inverter: Internal Option  |
| <a href="#">269426</a> | FR-A8AX<br>16-Bit-Digital-Input; BCD/Binary-Code; 24V DC; 5mA for FR-F/A800<br>Class 100100402: FA-Inverter: Internal Option                                       |
| <a href="#">269427</a> | FR-A8AY<br>Digital-/Analog Output; Output load: 24V DC; 0,1A for FR-F/A800<br>Class 100100402: FA-Inverter: Internal Option  |
| <a href="#">269428</a> | FR-A8AR<br>Relay output; 3 additional output relays for FR-A/F800<br>Class 100100402: FA-Inverter: Internal Option   |
| <a href="#">269431</a> | FR-A8NC<br>CC-Link Interface for FR-A/F800<br>Class 100100402: FA-Inverter: Internal Option  |
| <a href="#">269432</a> | FR-A8ND<br>DeviceNet Interface for FR-A/F800<br>Class 100100402: FA-Inverter: Internal Option  |
| <a href="#">270288</a> | FR-HC2-H30K KIT<br>Harmonic Converter 30 kW for Power Factor correction; 400V Class; KIT<br>Class 100100403: FA-Inverter: External Option                          |
| <a href="#">273102</a> | FR-A8NCE<br>CC-Link IE Field Interface for FR-A/F800<br>Class 100100402: FA-Inverter: Internal Option  |
| <a href="#">274514</a> | FR-A8NP<br>ProfibusDP Interface for FR-A/F800 with FR-A/F700 PPO types<br>Class 100100402: FA-Inverter: Internal Option  |
| <a href="#">274526</a> | FR-A8TAT<br>Adapter for control terminal of A/F700 to A/F800<br>Class 100100402: FA-Inverter: Internal Option  |
| <a href="#">275503</a> | FR Configurator-M+FR-Configurator2<br>FR-Configurator for 700 series; multi I + FR-Configurator2 for 800 series<br>Class 100101203: FA-Software: Software Inverter |
| <a href="#">277883</a> | FR-A8CN04<br>Heatsink Protrusion Attachment for FR-F/A840-00470/00620; for FR-A820-00770/0125<br>Class 100100403: FA-Inverter: External Option                     |
| <a href="#">283940</a> | FR-A8AZ<br>Analog Input/ output, Thermistor interface<br>Class 100100402: FA-Inverter: Internal Option   |
| <a href="#">284809</a> | A8NECT_2P<br>Ethercat 2port Interface for FR-A/F800<br>Class 100100402: FA-Inverter: Internal Option   |
| <a href="#">290115</a> | FR-A8NCN<br>Control Net Interface for FR-A800 series<br>Class 100100402: FA-Inverter: Internal Option  |
| <a href="#">290116</a> | FR-A8TR<br>Screw Terminal Block for FR-A/F800<br>Class 100100402: FA-Inverter: Internal Option   |
| <a href="#">294939</a> | FR-D-Sub9-A8NP-01<br>D-Sub9 Connection Adapter for FR-A8NP + Cover<br>Class 100100402: FA-Inverter: Internal Option  |
| <a href="#">296613</a> | FR-LU08-01<br>Clear text LCD Parameter unit for all units of 800 Series (IP55)<br>Class 100100403: FA-Inverter: External Option                                    |
| <a href="#">298663</a> | S-T50 AC100V<br>Magnetic contactor. 22kW; 2NO + 2NC; Us = AC 100V, 50Hz<br>Class 100101001: FA-MC: Magnetic Contactor  |
| <a href="#">298664</a> | S-T50 AC200V<br>Magnetic contactor. 22kW; 2NO + 2NC; Us = AC 200V, 50Hz<br>Class 100101001: FA-MC: Magnetic Contactor  |

| Material               | Description / Price List Text / Classification   |
|------------------------|--|
| <a href="#">298665</a> | S-T50 AC24V<br>Magnetic contactor. 22kW; 2NO + 2NC; Us = AC 24V, 50Hz<br>Class 100101001: FA-MC: Magnetic Contactor                              |
| <a href="#">298667</a> | S-T50 AC400V<br>Magnetic contactor. 22kW; 2NO + 2NC; Us = AC 400V, 50Hz<br>Class 100101001: FA-MC: Magnetic Contactor                            |
| <a href="#">307170</a> | FR-A8ERS-60<br>Optioncard to change Ethernet board to serial communication<br>Class 100100402: FA-Inverter: Internal Option                      |
| <a href="#">403133</a> | FR-A8AVP<br>Phase detection option board of FR-A/F800<br>Class 100100402: FA-Inverter: Internal Option   |
| <a href="#">403134</a> | FR-A8VPB-H<br>Phase detection transformer box for FR-A8AVP<br>Class 100100403: FA-Inverter: External Option                                      |
| <a href="#">409897</a> | FR-XC-H30K<br>Multifunction Regeneration Conv.;400V class;30kW<br>Class 100100403: FA-Inverter: External Option                                  |
| <a href="#">409918</a> | FR-XCL-H30K<br>Standalone reactor for FR-XC regeneration converter;400V;30 kW;Common bus reg.<br>Class 100100403: FA-Inverter: External Option   |
| <a href="#">409926</a> | FR-XCB-H22K<br>Reactor box-type 22 kW for FR-XC-H22K-PWM;400V;Harmonic suppression mode<br>Class 100100403: FA-Inverter: External Option         |
| <a href="#">487882</a> | FR-A8NCG<br>Plug-in Option for CC-Link IE TSN Communication Function<br>Class 100100402: FA-Inverter: Internal Option                            |
| <a href="#">500834</a> | FR-XCG-H30K<br>Standalone reactor for FR-XC regeneration converter; 400V class; 30kW;Reg.mode<br>Class 100100403: FA-Inverter: External Option   |
| <a href="#">587964</a> | RHF-5P 30-400-50-20-C<br>High efficient double-stage passive harmonic filter for THDi <5%;400V;50Hz;30kW<br>Class 100100404: FA-Inverter: Filter |
| <a href="#">591598</a> | RHF-8P 30-400-50-20-C<br>High efficient double-stage passive harmonic filter for THDi <8%;400V;50Hz;30kW<br>Class 100100404: FA-Inverter: Filter |