



MATERIAL FACT SHEET

297619 FR-A820-00490-E1-N6

General Data

Product Hierarchy	IAK24104
	INVERTER
	FR-A820 from 00046 to 04750
Ext. Material Group	10 STANDARD ITEM
ABC Indicator	B (Limited Availability from Stock)

e-shop: https://mitsubishi-electric-eshop.mee.com/mee/FA_IA/EUR/en/p/000000000000297619

FA-Inverter: Inverter

Series	FR-A SERIES
Type	FR-A800-E INVERTER
Minimum Rated Voltage (V)	200
Min. Permissible Voltage (V)	170
Maximum Rated Voltage (V)	240
Max. Permissible Voltage (V)	264
Current Type	AC
Phases	3
Rated Output Current SLD (A)	49
Rated Output Current LD (A)	45
Rated Output Current ND (A)	33
Rated Output Current HD (A)	24
Rated Motor Capacity SLD (kW)	11
Rated Motor Capacity LD (kW)	11
Rated Motor Capacity ND (kW)	7,5
Rated Motor Capacity HD (kW)	5,5
Frequency Range (Hz)	0,2-590
Control Method	MAGNETIC FLUX VECTOR CONTROL
Control Method (2)	PM SENSORLESS VECTOR CONTROL
Control Method (3)	REAL SENSORLESS VECTOR CONTROL
Control Method (4)	SOFT-PWM/HIGH FREQUENCY PWM
Control Method (5)	V/F CONTROL
Control Method (6)	VECTOR CONTROL (WITH FR-A8AP)
Motor Type	INDUCTION MOTOR, PM MOTOR
Brake Chopper ED (%)	-
Integrated EMC Filter	YES (OFF ON INITIAL SETTINGS)
Safe Torque Off (STO)	YES
Regenerative (4Q)	NO
Integrated DC Choke	NO
Display	FR-DU08
Display Type	5 DIGITS LED (12 SEGMENT)
PLC Function	YES
Program Memory	6K
Program Memory Unit	STEPS
Integrated Digital Inputs	12
Digital Outputs (Transistor)	5
Digital Outputs (Relay)	2
Integrated Analogue Inputs	3
Integrated Analogue Outputs	2
IO Type of Terminal Block	SPRING CLAMP
Expandable	YES
USB	1+1 MINI
Ethernet Port	1
Built-In Network	CC-LINK IE FIELD NETWORK
Built-In Network (2)	CC-LINK IE FIELD NETWORK BASIC
Built-In Network (3)	MODBUS/TCP
Leakage Current (mA)	22
Power Loss SLD (W)	525

Power Loss LD (W)	480
Power Loss ND (W)	350
Power Loss HD (W)	230
Standby Power Consumption (W)	-
Protection Class	IP20

Product Dimensions & Weight

Width (mm)	220
Height (mm)	324
Depth (mm)	170
Weight (kg)	7,52

Logistic Dimensions & Gross Weight

Length (cm)	27,5
Width (cm)	43,0
Height (cm)	24,5
Gross Weight (kg)	9,526
Volume (cdm)	28,971

Stock Data

Planned Delivery Time (Days)	268
------------------------------	-----

Life Cycle

Sales Start	30.05.2016
Predecessor	284529 / FR-A820-00490-1-N6

Additional Product Information

Binding Tariff Information	DEBTI-21865/22-1
BTI validity date	01.01.2026
Battery included	NO

Export Data

Legal Control (Dual Use List)	Not Listed
Country of Origin	Japan (JP)
Preference Status (Supplier Declaration)	Non EU

Environmental

REACH Limit Exceeded	YES
REACH Substance CAS Number	12626-81-2
REACH Substance CAS Number (2)	127-19-5
REACH Substance CAS Number (3)	1317-36-8
REACH Substance CAS Number (4)	13560-89-9
REACH Substance CAS Number (5)	15571-58-1
REACH Substance CAS Number (6)	7439-92-1
REACH Substance CAS Number (7)	96-45-7
Dangerous Goods Class	NO
Dangerous Goods Identifier	NO
WEEE	B2B

Conformity

CE	COMPLIANT
UL/cUL	COMPLIANT
EAC	COMPLIANT
UKCA	COMPLIANT

Documentation & Media Data

Manual URL Indicator	https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&doc-cats=bltdae25c2bd5f2ff94&q=FR-A820-00490-E1-N6&doc-lang=en
Certificates URL Indicator	https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&doc-cats=blt8050dd1408c11cc2&q=FR-A820-00490-E1-N6&doc-lang=en
CAD URL Indicator	https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&doc-cats=blt26ecc97a31a841c1&q=FR-A820-00490-E1-N6&doc-lang=en
Network configuration file URL	https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&doc-cats=blte8cf990c7c524b4e&q=FR-A820-00490-E1-N6&doc-lang=en

Product Packaging

Cardboard (g)	1650
Other paper (g)	0
Aluminum (g)	0

Steel (g)	0
Styrofoam (g)	0
Other plastic (g)	10
Wood (g)	0
Glass (g)	0
Others (g)	0

Spare parts

Material	Description	Quantity	Unit
282932	FR-A840/842/846-ALL TERMINAL BLOCK A80TA	1	PC
282933	FR-A840-00170-00250/A846-ALL CBL MA-CPU	1	PC
283446	FR-A840-00170-00250-2-60 FAN	2	PC
283686	FR-A840-00170/00250-2-60 COVER LOWER FR.	1	PC
283688	FR-A840-00170/00250-2-60 COVER FAN	1	PC
487545	FR-A820-00490 PCB MA	1	PC

Compatible products

Material	Description / Price List Text / Classification
167612	FR-RJ45-HUB10 Distribution Module for RJ45; 10 way Class 100100403: FA-Inverter: External Option
167613	FR-RJ45-HUB4 Distribution Module for RJ45; 4 way Class 100100403: FA-Inverter: External Option
167614	FR-RJ45-TR Terminal Resistor Plug RJ45 Class 100100403: FA-Inverter: External Option
209739	FFR-SI-32A-SS1 Sinusfilter for 200/230/400V Inverters;max. 32A;FT=4-16kHz;(W*H*D) 210*260*135mm Class 100100404: FA-Inverter: Filter
209757	FFR-DT-47A-SS1 du/dt Filter for 400V Inverters; max. 47A; FT=2-16kHz; (W*H*D) 155*195*110mm Class 100100404: FA-Inverter: Filter
221540	USB-CAB-5M USB 2.0 connection cabel, plug USB A to plug USB B (mini), 5m Class 100100303: FA-HMI: Cable
253073	NF63-SV 3P 50A Circuit breaker 3pole. In = 50A; Icu = Ics = 7,5kA at AC 440V Class 100100901: FA-MCCB: Moulded-Case Circuit Breaker
254750	NF63-SV 3P 60A Circuit breaker 3pole. In = 60A; Icu = Ics = 7,5kA at AC 440V Class 100100901: FA-MCCB: Moulded-Case Circuit Breaker
254786	NF63-HV 3P 50A Circuit breaker 3pole. In = 50A; Icu / Ics = 10 / 8kA at AC 440V Class 100100901: FA-MCCB: Moulded-Case Circuit Breaker
254787	NF63-HV 3P 60A Circuit breaker 3pole. In = 60A; Icu / Ics = 10 / 8kA at AC 440V Class 100100901: FA-MCCB: Moulded-Case Circuit Breaker
262948	A8NDPV1 Profibus DPV1 with Dsub Interface for FR-A/F800 Class 100100402: FA-Inverter: Internal Option
262949	A8NPRT_2P Profinet 2port Interface for FR-A/F800 with Drive Profile Class 100100402: FA-Inverter: Internal Option
262950	A8NEIP_2P EtherNet/IP 2port Interface for FR-A/F800 Class 100100402: FA-Inverter: Internal Option
269426	FR-A8AX 16-Bit-Digital-Input; BCD/Binary-Code; 24V DC; 5mA for FR-F/A800 Class 100100402: FA-Inverter: Internal Option
269427	FR-A8AY Digital-/Analog Output; Output load: 24V DC; 0,1A for FR-F/A800 Class 100100402: FA-Inverter: Internal Option
269428	FR-A8AR Relay output; 3 additional output relays for FR-A/F800 Class 100100402: FA-Inverter: Internal Option
269429	FR-A8AP Incremental Encoder Feedback for FR-A800 Class 100100402: FA-Inverter: Internal Option

Material	Description / Price List Text / Classification
269430	FR-A8AL Incremental encoder feedback terminal block for FR-A800 Class 100100402: FA-Inverter: Internal Option
269431	FR-A8NC CC-Link Interface for FR-A/F800 Class 100100402: FA-Inverter: Internal Option
269432	FR-A8ND DeviceNet Interface for FR-A/F800 Class 100100402: FA-Inverter: Internal Option
273102	FR-A8NCE CC-Link IE Field Interface for FR-A/F800 Class 100100402: FA-Inverter: Internal Option
274514	FR-A8NP ProfibusDP Interface for FR-A/F800 with FR-A/F700 PPO types Class 100100402: FA-Inverter: Internal Option
274526	FR-A8TAT Adapter for control terminal of A/F700 to A/F800 Class 100100402: FA-Inverter: Internal Option
275503	FR Configurator-M+FR-Configurator2 FR-Configurator for 700 series; multi I + FR-Configurator2 for 800 series Class 100101203: FA-Software: Software Inverter
283575	FFR-HEL-7.5K-E1 DC Link choke for 200V Inverter; 7,5kW; 0,77mH; 34A Class 100100406: FA-Inverter: Choke
283939	FR-A8APR Resolver interface/orientation control/Resolver feedback control/vector control Class 100100402: FA-Inverter: Internal Option
283940	FR-A8AZ Analog Input/ output, Thermistor interface Class 100100402: FA-Inverter: Internal Option
284809	A8NECT_2P Ethercat 2port Interface for FR-A/F800 Class 100100402: FA-Inverter: Internal Option
285244	FR-A8TP Incremental Encoder Feedback Terminal Block for FR-A800 Class 100100402: FA-Inverter: Internal Option
294939	FR-D-Sub9-A8NP-01 D-Sub9 Connection Adapter for FR-A8NP + Cover Class 100100402: FA-Inverter: Internal Option
297422	FR-A8APS Absolute Encoder Feedback for FR-A800 (EnDat) Class 100100402: FA-Inverter: Internal Option
298153	FR-A8NCA CANopen Interface for FR-A800 Class 100100402: FA-Inverter: Internal Option
298153	FR-A8NCA CANopen Interface for FR-A800 Class 100100402: FA-Inverter: Internal Option
298656	S-T35 AC100V Magnetic contactor. 18,5kW; 2NO + 2NC; Us = AC 100V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298656	S-T35 AC100V Magnetic contactor. 18,5kW; 2NO + 2NC; Us = AC 100V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298657	S-T35 AC200V Magnetic contactor. 18,5kW; 2NO + 2NC; Us = AC 200V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298657	S-T35 AC200V Magnetic contactor. 18,5kW; 2NO + 2NC; Us = AC 200V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298658	S-T35 AC24V Magnetic contactor. 18,5kW; 2NO + 2NC; Us = AC 24V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298658	S-T35 AC24V Magnetic contactor. 18,5kW; 2NO + 2NC; Us = AC 24V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298659	S-T35 AC300V Magnetic contactor. 18,5kW; 2NO + 2NC; Us = AC 300V, 50Hz Class 100101001: FA-MC: Magnetic Contactor

Material	Description / Price List Text / Classification
298659	S-T35 AC300V Magnetic contactor. 18,5kW; 2NO + 2NC; Us = AC 300V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298660	S-T35 AC400V Magnetic contactor. 18,5kW; 2NO + 2NC; Us = AC 400V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298660	S-T35 AC400V Magnetic contactor. 18,5kW; 2NO + 2NC; Us = AC 400V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298661	S-T35 AC48V Magnetic contactor. 18,5kW; 2NO + 2NC; Us = AC 48V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298661	S-T35 AC48V Magnetic contactor. 18,5kW; 2NO + 2NC; Us = AC 48V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298662	S-T35 AC500V Magnetic contactor. 18,5kW; 2NO + 2NC; Us = AC 500V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298662	S-T35 AC500V Magnetic contactor. 18,5kW; 2NO + 2NC; Us = AC 500V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
307170	FR-A8ERS-60 Optioncard to change Ethernet board to serial communication Class 100100402: FA-Inverter: Internal Option
307170	FR-A8ERS-60 Optioncard to change Ethernet board to serial communication Class 100100402: FA-Inverter: Internal Option
403614	FR-A8APA SinCos Encoder Feedback for FR-A800 Class 100100402: FA-Inverter: Internal Option