



MATERIAL FACT SHEET

297580 FR-A840-01800-E2-60

General Data

Product Hierarchy	IAK24102
	INVERTER
	FR-A840 from 00770 to 01800
Ext. Material Group	10 STANDARD ITEM
ABC Indicator	C (Non-Stock Material / Make-to-Order)

e-shop: https://mitsubishi-electric-eshop.mee.com/mee/FA_1A/EUR/en/p/0000000000000297580

Product Components

307185 / FR-AF840-01800-60	1 pc required
307202 / FR-CA80-01-E2-60	1 pc required

FA-Inverter: Inverter

Series	FR-A SERIES
Type	FR-A800-E INVERTER
Minimum Rated Voltage (V)	380
Min. Permissible Voltage (V)	323
Maximum Rated Voltage (V)	500
Max. Permissible Voltage (V)	550
Current Type	AC
Phases	3
Rated Output Current SLD (A)	180
Rated Output Current LD (A)	144
Rated Output Current ND (A)	110
Rated Output Current HD (A)	86
Rated Motor Capacity SLD (kW)	75/90
Rated Motor Capacity LD (kW)	75
Rated Motor Capacity ND (kW)	55
Rated Motor Capacity HD (kW)	45
Frequency Range (Hz)	0,2–590
Control Method	MAGNETIC FLUX VECTOR CONTROL
Control Method (2)	PM SENSORLESS VECTOR CONTROL
Control Method (3)	REAL SENSORLESS VECTOR CONTROL
Control Method (4)	SOFT-PWM/HIGH FREQUENCY PWM
Control Method (5)	V/F CONTROL
Control Method (6)	VECTOR CONTROL (WITH FR-A8AP)
Motor Type	INDUCTION MOTOR, PM MOTOR
Integrated EMC Filter	YES
Safe Torque Off (STO)	YES
Regenerative (4Q)	NO
Integrated DC Choke	NO
Display	FR-DU08
Display Type	5 DIGITS LED (12 SEGMENT)
PLC Function	YES
Program Memory	6K
Program Memory Unit	STEPS
Integrated Digital Inputs	12
Digital Outputs (Transistor)	5
Digital Outputs (Relay)	2
Integrated Analogue Inputs	3
Integrated Analogue Outputs	2
IO Type of Terminal Block	SPRING CLAMP
Expandable	YES
RS-485	OPTIONAL
USB	1+1 MINI
Ethernet Port	1
Built-In Network	CC-LINK IE FIELD NETWORK

Built-In Network (2)	CC-LINK IE FIELD NETWORK BASIC
Built-In Network (3)	MODBUS/TCP
Leakage Current (mA)	35(DELTA) / 2(STAR)
Power Loss SLD (W)	2000
Power Loss LD (W)	1640
Power Loss ND (W)	1290
Power Loss HD (W)	1060
Standby Power Consumption (W)	28
Protection Class	IP00

Product Dimensions & Weight

Width (mm)	435
Height (mm)	550
Depth (mm)	250
Weight (kg)	43

Logistic Dimensions & Gross Weight

Length (cm)	60,0
Width (cm)	57,0
Height (cm)	40,0
Gross Weight (kg)	46,000
Volume (cdm)	136,800

Stock Data

Planned Delivery Time (Days)	100
------------------------------	-----

Life Cycle

Sales Start	30.05.2016
Predecessor	266755 / FR-A840-01800-2-60

Additional Product Information

Binding Tariff Information	DEBTI-21865/22-1
BTI validity date	01.01.2026
Battery included	NO

Export Data

Legal Control (Dual Use List)	Not Listed
Country of Origin	China (CN)
Preference Status (Supplier Declaration)	Non EU

Environmental

REACH Limit Exceeded	NO
Dangerous Goods Class	NO
Dangerous Goods Identifier	NO
RoHS Compliance	COMPLIANT
WEEE	B2B

Conformity

CE	COMPLIANT
UL/cUL	COMPLIANT
EAC	COMPLIANT
Shipping Approvals	ABS,BV,DNV GL,LR,NK
UKCA	COMPLIANT

Documentation & Media Data

Manual URL Indicator	https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&doc-cats=bltdae25c2bd5f2ff94&q=FR-A840-01800-E2-60&doc-lang=en
Certificates URL Indicator	https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&doc-cats=blt8050dd1408c11cc2&q=FR-A840-01800-E2-60&doc-lang=en
CAD URL Indicator	https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&doc-cats=blt26ecc97a31a841c1&q=FR-A840-01800-E2-60&doc-lang=en
Network configuration file URL	https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&doc-cats=blte8cf990c7c524b4e&q=FR-A840-01800-E2-60&doc-lang=en

Product Packaging

Cardboard (g)	4908,8
Other paper (g)	0
Aluminum (g)	0
Steel (g)	0

Styrofoam (g)	0
Other plastic (g)	155
Wood (g)	0
Glass (g)	0
Others (g)	0

Spare parts

Material	Description	Quantity	Unit
692927	FR-A840-01800-2-60 PCB MA	1	PC
282906	FR-A840-00930-01800-2-60 PCB AUX	1	PC
307202	FR-CA80-01-E2-60	1	PC
282932	FR-A840/842/846-ALL TERMINAL BLOCK A80TA	1	PC
282940	FR-A840/842/CC2-ALL CASE CPU	1	PC
283435	FR-A840-00930-01800-2-60 DM	3	PC
283439	FR-A840-00930-01800-2-60 THYRISTORMODULE	1	PC
676513	FR-A840-00930-01800 BREAKING IGBT	1	PC
283443	FR-A840-01800-2-60 IGBT CM300DY-24S	3	PC
283450	FR-A840-00470-01800-2-60 FAN	3	PC
283462	FR-A840-00930-01800-2-60 INRUSH RES.	1	PC
283471	FR-A840-01800-2-60 DCCT	1	PC
283484	FR-A840-00770-2-60 OR BIGGER CBL MA-CPU	1	PC
283591	FR-A840-01800-2-60 CAPACITOR	4	PC
283707	FR-A840-00930-12120-2-60 COVER	1	PC
283708	FR-A840-00930-01800-2-60 CASE FAN	3	PC
283709	FR-A840-00930-01800-2-60 COVER FAN	3	PC
283710	FR-A840-00930-01800-2-60 COVER TERMINAL	1	PC

Compatible products

Material	Description / Price List Text / Classification
70727	FR-A5 CBL 1 Cable for connecting Inverter and Programming panel; 1m Class 100100405: FA-Inverter: Cable
70728	FR-A5 CBL 2,5 Cable for connecting Inverter and Programming panel; 2,5m Class 100100405: FA-Inverter: Cable
70729	FR-A5 CBL 5 Cable for connecting Inverter and Programming panel; 5m Class 100100405: FA-Inverter: Cable
167612	FR-RJ45-HUB10 Distribution Module for RJ45; 10 way Class 100100403: FA-Inverter: External Option
167613	FR-RJ45-HUB4 Distribution Module for RJ45; 4 way Class 100100403: FA-Inverter: External Option
167614	FR-RJ45-TR Terminal Resistor Plug RJ45 Class 100100403: FA-Inverter: External Option
193683	FFR-BS-01800-180A-SF100 Radio Noise Filter for FR-A&F-00930-01800; C1 20m; C2 100m Class 100100404: FA-Inverter: Filter
209744	FFR-SI-116A-SS1 Sinusfilter for 200/400V Inverters; max. 116A; FT=4-16kHz; (W*H*D) 300*345*237mm Class 100100404: FA-Inverter: Filter
209759	FFR-DT-124A-SS1 du/dt Filter for 400V Inverters; max. 124A; FT=2-16kHz; (W*H*D) 190*170*150mm Class 100100404: FA-Inverter: Filter
212210	RUFC40 (000100) Brake Resistor Class 100100403: FA-Inverter: External Option
221540	USB-CAB-5M USB 2.0 connection cabel, plug USB A to plug USB B (mini), 5m Class 100100303: FA-HMI: Cable
238356	FFR-HEL-H55K-E DC Link choke for 400V Inverter; 55kW; 0,68mH; 99A Class 100100406: FA-Inverter: Choke
255077	NF250-SV 3P 150A Circuit breaker 3pole. In = 150A; Icu = Ics = 36kA at AC 440V Class 100100901: FA-MCCB: Moulded-Case Circuit Breaker

Material	Description / Price List Text / Classification
255080	NF250-SV 3P 200A Circuit breaker 3pole. In = 200A; Icu = Ics = 36kA at AC 440V Class 100100901: FA-MCCB: Moulded-Case Circuit Breaker
262948	A8NDPV1 Profibus DPV1 with Dsub Interface for FR-A/F800 Class 100100402: FA-Inverter: Internal Option
262949	A8NPRT_2P Profinet 2port Interface for FR-A/F800 with Drive Profile Class 100100402: FA-Inverter: Internal Option
262950	A8NEIP_2P EtherNet/IP 2port Interface for FR-A/F800 Class 100100402: FA-Inverter: Internal Option
269426	FR-A8AX 16-Bit-Digital-Input; BCD/Binary-Code; 24V DC; 5mA for FR-F/A800 Class 100100402: FA-Inverter: Internal Option
269427	FR-A8AY Digital-/Analog Output; Output load: 24V DC; 0,1A for FR-F/A800 Class 100100402: FA-Inverter: Internal Option
269428	FR-A8AR Relay output; 3 additional output relays for FR-A/F800 Class 100100402: FA-Inverter: Internal Option
269429	FR-A8AP Incremental Encoder Feedback for FR-A800 Class 100100402: FA-Inverter: Internal Option
269430	FR-A8AL Incremental encoder feedback terminal block for FR-A800 Class 100100402: FA-Inverter: Internal Option
269431	FR-A8NC CC-Link Interface for FR-A/F800 Class 100100402: FA-Inverter: Internal Option
269432	FR-A8ND DeviceNet Interface for FR-A/F800 Class 100100402: FA-Inverter: Internal Option
273102	FR-A8NCE CC-Link IE Field Interface for FR-A/F800 Class 100100402: FA-Inverter: Internal Option
274514	FR-A8NP ProfibusDP Interface for FR-A/F800 with FR-A/F700 PPO types Class 100100402: FA-Inverter: Internal Option
274525	FR-LU08 Clear text LCD Parameter unit for all units of 800 Series Class 100100403: FA-Inverter: External Option
274526	FR-A8TAT Adapter for control terminal of A/F700 to A/F800 Class 100100402: FA-Inverter: Internal Option
275503	FR Configurator-M+FR-Configurator2 FR-Configurator for 700 series; multi I + FR-Configurator2 for 800 series Class 100101203: FA-Software: Software Inverter
277945	FR-A8CN06 Heatsink Protrusion Attachment for FR-F/A840-00930 bis 01800; for FR-A820-01870/ Class 100100403: FA-Inverter: External Option
283939	FR-A8APR Resolver interface/orientation control/Resolver feedback control/vector control Class 100100402: FA-Inverter: Internal Option
283940	FR-A8AZ Analog Input/ output, Thermistor interface Class 100100402: FA-Inverter: Internal Option
284809	A8NECT_2P Ethercat 2port Interface for FR-A/F800 Class 100100402: FA-Inverter: Internal Option
285244	FR-A8TP Incremental Encoder Feedback Terminal Block for FR-A800 Class 100100402: FA-Inverter: Internal Option
289335	FR-A8NS SSCNet Interface for FR-A800 Class 100100402: FA-Inverter: Internal Option
294939	FR-D-Sub9-A8NP-01 D-Sub9 Connection Adapter for FR-A8NP + Cover Class 100100402: FA-Inverter: Internal Option

Material	Description / Price List Text / Classification
296225	FR-BAL-B3-55K Input reactor 3ph, 400V, In= 106A, Pn=55kW, L1=0,221mH Class 100100406: FA-Inverter: Choke
296613	FR-LU08-01 Clear text LCD Parameter unit for all units of 800 Series (IP55) Class 100100403: FA-Inverter: External Option
297422	FR-A8APS Absolute Encoder Feedback for FR-A800 (EnDat) Class 100100402: FA-Inverter: Internal Option
298153	FR-A8NCA CANopen Interface for FR-A800 Class 100100402: FA-Inverter: Internal Option
298684	S-T100 AC100V Magnetic contactor. 55kW; 2NO + 2NC; Us = AC 100V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298684	S-T100 AC100V Magnetic contactor. 55kW; 2NO + 2NC; Us = AC 100V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298685	S-T100 AC200V Magnetic contactor. 55kW; 2NO + 2NC; Us = AC 200V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298685	S-T100 AC200V Magnetic contactor. 55kW; 2NO + 2NC; Us = AC 200V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298686	S-T100 AC24V Magnetic contactor. 55kW; 2NO + 2NC; Us = AC 24V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298686	S-T100 AC24V Magnetic contactor. 55kW; 2NO + 2NC; Us = AC 24V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298687	S-T100 AC300V Magnetic contactor. 55kW; 2NO + 2NC; Us = AC 300V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298687	S-T100 AC300V Magnetic contactor. 55kW; 2NO + 2NC; Us = AC 300V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298688	S-T100 AC400V Magnetic contactor. 55kW; 2NO + 2NC; Us = AC 400V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298688	S-T100 AC400V Magnetic contactor. 55kW; 2NO + 2NC; Us = AC 400V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298689	S-T100 AC48V Magnetic contactor. 55kW; 2NO + 2NC; Us = AC 48V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
298689	S-T100 AC48V Magnetic contactor. 55kW; 2NO + 2NC; Us = AC 48V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
307170	FR-A8ERS-60 Optioncard to change Ethernet board to serial communication Class 100100402: FA-Inverter: Internal Option
307170	FR-A8ERS-60 Optioncard to change Ethernet board to serial communication Class 100100402: FA-Inverter: Internal Option
307185	FR-AF840-01800-60 Inverter Body AC; Pn: 45-90kW; 3x380-500V;In max: 180A;(55kW; 110A); IP00 Class 100100401: FA-Inverter: Inverter
307202	FR-CA80-01-E2-60 Control Card for FR-A840-00770 -01800 Ethernet Version Class 100100402: FA-Inverter: Internal Option
403614	FR-A8APA SinCos Encoder Feedback for FR-A800 Class 100100402: FA-Inverter: Internal Option
591580	RHF-5P 55-400-50-20-C High efficient double-stage passive harmonic filter for THDi <5%;400V;50Hz;55kW Class 100100404: FA-Inverter: Filter
591601	RHF-8P 55-400-50-20-C High efficient double-stage passive harmonic filter for THDi <8%;400V;50Hz;55kW Class 100100404: FA-Inverter: Filter