



MATERIAL FACT SHEET

577192 FR-E840-0026SCEPA-60

General Data

Product Hierarchy	IAK24802
	INVERTER
	FR-E840
Ext. Material Group	10 STANDARD ITEM
ABC Indicator	C (Non-Stock Material / Make-to-Order)

e-shop: <https://emea-fa.mitsubishielectric.com/fa/shop/material-page/00000000000577192>

FA-Inverter: Inverter

Series	FR-E800 SERIES
Type	FR-E800-ETH SAFETY CONTROL
Minimum Rated Voltage (V)	380
Min. Permissible Voltage (V)	323
Maximum Rated Voltage (V)	480
Max. Permissible Voltage (V)	528
Current Type	AC
Phases	3
Rated Output Current LD (A)	3,5
Rated Output Current ND (A)	2,6
Rated Motor Capacity LD (kW)	1,5
Rated Motor Capacity ND (kW)	0,75
Frequency Range (Hz)	0,2-590
Control Method	MAGNETIC FLUX VECTOR CONTROL
Control Method (2)	PM SENSORLESS VECTOR CONTROL
Control Method (3)	REAL SENSORLESS VECTOR CONTROL
Control Method (4)	V/F CONTROL
Motor Type	INDUCTION MOTOR, PM MOTOR
Brake Chopper ED (%)	100
Integrated EMC Filter	NO
Safe Torque Off (STO)	YES
Regenerative (4Q)	NO
Integrated DC Choke	NO
Display	BUILT-IN
Display Type	4 DIGITS LED
PLC Function	YES
Program Memory	2K
Program Memory Unit	STEPS
Integrated Digital Inputs	0
Digital Outputs (Transistor)	0
Digital Outputs (Relay)	1
Integrated Analogue Inputs	2
Integrated Analogue Outputs	0
IO Type of Terminal Block	SPRING CLAMP
Expandable	YES
RS-485	NO
USB	1 (MINI B)
Ethernet Port	2
Built-In Network	BACNET/IP
Built-In Network (2)	CC-LINK IE FIELD BASIC
Built-In Network (3)	CC-LINK IE TSN
Built-In Network (4)	ETHERNET/IP
Built-In Network (5)	MODBUS/TCP
Leakage Current (mA)	1,2
Power Loss LD (W)	56
Power Loss ND (W)	39
Standby Power Consumption (W)	-
Protection Class	IP20

Product Dimensions & Weight

Width (mm)	108
Height (mm)	128
Depth (mm)	129,5
Weight (kg)	1,2

Logistic Dimensions & Gross Weight

Length (cm)	21,0
Width (cm)	13,0
Height (cm)	20,0
Gross Weight (kg)	1,429
Volume (cdm)	5,460

Stock Data

Planned Delivery Time (Days)	175
------------------------------	-----

Life Cycle

Sales Start	09.11.2020
Predecessor	No Predecessor

Additional Product Information

Battery included	NO
Product Code	INV(EXCEPT VECTOR INV)

Export Data

Commodity Code	85044095
Legal Control (Dual Use List)	Not Listed
Country of Origin	Japan (JP)
Preference Status (Supplier Declaration)	Non EU

Environmental

REACH Limit Exceeded	YES
REACH Substance CAS Number	-
REACH Substance CAS Number (2)	119313-12-1
REACH Substance CAS Number (3)	1317-36-8
REACH Substance CAS Number (4)	540-97-6
REACH Substance CAS Number (5)	541-02-6
REACH Substance CAS Number (6)	556-67-2
REACH Substance CAS Number (7)	71868-10-5
REACH Substance CAS Number (8)	7439-92-1
Dangerous Goods Class	NO
Dangerous Goods Identifier	NO
RoHS Compliance	COMPLIANT
WEEE	B2B

Conformity

CE	COMPLIANT
UL/cUL	COMPLIANT
EAC	COMPLIANT
UKCA	COMPLIANT

Documentation & Media Data

Manual URL Indicator	https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&doc-cats=bltdae25c2bd5f2ff94&q=FR-E840-0026SCEPA-60&doc-lang=en
Certificates URL Indicator	https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&doc-cats=blt6050dd1408c11cc2&q=FR-E840-0026SCEPA-60&doc-lang=en
CAD URL Indicator	https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&doc-cats=blt26ecc97a31a841c1&q=FR-E840-0026SCEPA-60&doc-lang=en
Network configuration file URL	https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&doc-cats=blte8cf990c7c524b4e&q=FR-E840-0026SCEPA-60&doc-lang=en

Product Packaging

Cardboard (g)	800
Other paper (g)	0
Aluminum (g)	0
Steel (g)	0
Styrofoam (g)	0
Other plastic (g)	10

Wood (g)	0
Glass (g)	0
Others (g)	0

Spare parts

Material	Description	Quantity	Unit
600477	FR-E840-0026-4-0.75K PCB MA	1	PC
611070	FR-E840-0026EPA(B)-60 PCB GA	1	PC
611135	FR-E840-SCEPB-60 PCB TA	1	PC
611139	FR-E800-(SC)EPA(B) parameter unit	1	PC
611140	FR-E800-3,7K CBL CA	1	PC
611163	FR-E820-SCEPB-60 PCB TA	1	PC
764268	FR-E860 PRINTED WIRE BOARD TC103A732G51	1	PC

Compatible products

Material	Description / Price List Text / Classification
703072	EM-AMF 0.75KW 330V 100HZ PM Motor; 0.75kW; Flange type; 3000r/min Class 100100410: FA-Inverter: Motor
703073	EM-AMFW 0.75KW 330V 100HZ PM Motor; 0.75kW; Flange type; IP65; 3000r/min Class 100100410: FA-Inverter: Motor
703074	EM-AMFT 0.75KW 330V 100HZ PM Motor; 0.75kW; Flange type; Terminal Block; 3000r/min Class 100100410: FA-Inverter: Motor
703075	EM-AMFB 0.75KW 330V 100HZ PM Motor; 0.75kW; Flange type; With brake; 3000r/min Class 100100410: FA-Inverter: Motor
703076	EM-AMFBW 0.75KW 330V 100HZ PM Motor; 0.75kW; Flange type; With brake; IP65; 3000r/min Class 100100410: FA-Inverter: Motor
703077	EM-AMFBT 0.75KW 330V 100HZ PM Motor; 0.75kW; Flange type; Terminal Block; With brake; 3000r/min Class 100100410: FA-Inverter: Motor
703078	EM-AMFK 0.75KW 330V 100HZ PM Motor; 0.75kW; Flange type; With key; 3000r/min Class 100100410: FA-Inverter: Motor
703079	EM-AMFKW 0.75KW 330V 100HZ PM Motor; 0.75kW; Flange type; With key; IP65; 3000r/min Class 100100410: FA-Inverter: Motor
703080	EM-AMFKT 0.75KW 330V 100HZ PM Motor; 0.75kW; Flange type; Terminal Block; With key; 3000r/min Class 100100410: FA-Inverter: Motor
703081	EM-AMFBK 0.75KW 330V 100HZ PM Motor; 0.75kW; Flange type; With brake; With key; 3000r/min Class 100100410: FA-Inverter: Motor
703082	EM-AMFBKW 0.75KW 330V 100HZ PM Motor; 0.75kW; Flange type; With brake; With key; IP65; 3000r/min Class 100100410: FA-Inverter: Motor
703083	EM-AMFBKT 0.75KW 330V 100HZ PM Motor; 0.75kW; Flange type; Terminal Block; With brake; With key; 3000r/min Class 100100410: FA-Inverter: Motor