



## MATERIAL FACT SHEET

### 301923 FX5U-64MR/DS

#### General Data

Product Hierarchy	IAD21701
	Compact PLC
	FX5U CPU
Ext. Material Group	10 STANDARD ITEM
ABC Indicator	A (Available from Stock)

e-shop: <https://emea-fa.mitsubishielectric.com/fa/shop/material-page/00000000000301923>

#### FA-COM PLC: Main Unit

Series	MELSEC IQ-F SERIES
Type	FX5U
Power Supply (V)	24
Current Type	DC
Program Memory	64K STEPS
Program Memory Unit	FLASH
Integrated Digital Inputs	32
Integrated Digital Outputs	32
Integrated Analogue Inputs	2
Output Type	RELAY
Local I/O Points	256
Local + Remote I/O Points	512
Expandable	YES
Cycle Time LD (ns)	34
Cycle Time MOV (ns)	34
Ethernet Port	1
RS-485	1
Power Consumption (W)	40
Buffer Battery	OPTION
Protection Class	IP10
Min. Ambient Temperature (°C)	-20
Max. Ambient Temperature (°C)	55

#### Product Dimensions & Weight

Width (mm)	220
Height (mm)	90
Depth (mm)	83
Weight (kg)	1

#### Logistic Dimensions & Gross Weight

Length (cm)	28,5
Width (cm)	12,5
Height (cm)	11,0
Gross Weight (kg)	1,206
Volume (cdm)	3,919

#### Stock Data

Planned Delivery Time (Days)	91
------------------------------	----

#### Life Cycle

Sales Start	01.11.2016
Predecessor	No Predecessor

#### Additional Product Information

Binding Tariff Information	DEBTI-10856/21-1
BTI validity date	10.10.2024
Battery included	NO

Product Code	PLC(HIMEJI)
--------------	-------------

### Export Data

Commodity Code	85371091
Legal Control (Dual Use List)	Not Listed
Country of Origin	Japan (JP)
Preference Status (Supplier Declaration)	Non EU

### Environmental

REACH Limit Exceeded	YES
REACH Substance CAS Number	<a href="#">108-78-1</a>
REACH Substance CAS Number (2)	<a href="#">119313-12-1</a>
REACH Substance CAS Number (3)	<a href="#">12060-00-3</a>
REACH Substance CAS Number (4)	<a href="#">1303-86-2</a>
REACH Substance CAS Number (5)	<a href="#">629-14-1</a>
REACH Substance CAS Number (6)	<a href="#">71868-10-5</a>
REACH Substance CAS Number (7)	<a href="#">7439-92-1</a>
Dangerous Goods Class	NO
Dangerous Goods Identifier	NO
RoHS Compliance	COMPLIANT
WEEE	B2B

### Conformity

CE	COMPLIANT
UL/cUL	COMPLIANT
EAC	NON-COMPLIANT
Shipping Approvals	ABS,BV,DNV GL,KR,LR,NK,RINA
UKCA	COMPLIANT

### Documentation & Media Data

Manual URL Indicator	<a href="https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=bltdae25c2bd5f2ff94&amp;q=FX5U-64MR/DS&amp;doc-lang=en">https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=bltdae25c2bd5f2ff94&amp;q=FX5U-64MR/DS&amp;doc-lang=en</a>
Certificates URL Indicator	<a href="https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=blt8050dd1408c11cc2&amp;q=FX5U-64MR/DS&amp;doc-lang=en">https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=blt8050dd1408c11cc2&amp;q=FX5U-64MR/DS&amp;doc-lang=en</a>
CAD URL Indicator	<a href="https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=blt26ecc97a31a841c1&amp;q=FX5U-64MR/DS&amp;doc-lang=en">https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=blt26ecc97a31a841c1&amp;q=FX5U-64MR/DS&amp;doc-lang=en</a>

### Product Packaging

Cardboard (g)	210
Other paper (g)	0
Aluminum (g)	0
Steel (g)	0
Styrofoam (g)	0
Other plastic (g)	1
Wood (g)	0
Glass (g)	0
Others (g)	0

### Spare parts

Material	Description	Quantity	Unit
<a href="#">574516</a>	FX5U-64/80MR/DS PCB POWER	1	PC

### Compatible products

Material	Description / Price List Text / Classification
<a href="#">165286</a>	FX3U-32BL Battery Battery for PLC types FX3 / FX5 Class 100100112: FA-COM PLC: Spare Part
<a href="#">165286</a>	FX3U-32BL Battery Battery for PLC types FX3 / FX5 Class 100101303: FA-OTHERS: Battery
<a href="#">169507</a>	FX3U-1PSU-5V PLC, FX Series Power supply module for 5V bus Class 100100111: FA-COM PLC: Other Option
<a href="#">280509</a>	FX5-1PSU-5V FX5;Power Supply Unit 5VDC Bus Class 100100111: FA-COM PLC: Other Option
<a href="#">280510</a>	FX5-CNV-BUS FX5;FX3 Bus Conversion Unit Class 100100111: FA-COM PLC: Other Option

Material	Description / Price List Text / Classification
<a href="#">280511</a>	FX5-232-BD FX5;Serial Communication Board;RS-232 Class 100100107: FA-COM PLC: Serial Com Module
<a href="#">280512</a>	FX5-485-BD FX5;Serial Communication Board;RS-485 Class 100100107: FA-COM PLC: Serial Com Module
<a href="#">280515</a>	FX5-422-BD-GOT FX5;Serial Communication Board;RS-422;Communication to GOT only Class 100100107: FA-COM PLC: Serial Com Module
<a href="#">283557</a>	FX5-CNV-IFC FX5UC;FX5U Bus Converter Class 100100111: FA-COM PLC: Other Option
<a href="#">283558</a>	FX5-CNV-BUSC FX5UC;FX3 Bus Conversion Unit Class 100100111: FA-COM PLC: Other Option
<a href="#">284378</a>	GX Works3 2L-USB PLC Programming Software for MELSEC iQ-R/F, English, 2 Licences USB Class 100101201: FA-Software: Software PLC
<a href="#">284379</a>	GX Works3 5L-USB PLC Programming Software for MELSEC iQ-R/F, English, 5 Licences USB Class 100101201: FA-Software: Software PLC
<a href="#">286227</a>	iQ Works 2L-USB iQ Works V2.0,inc Navigator/GX/GT/MT Works/RT Toolbox3 inc SIM,Eng,2 Licence USB Class 100101201: FA-Software: Software PLC
<a href="#">286228</a>	iQ Works 5L-USB iQ Works V2.0,inc Navigator/GX/GT/MT Works/RT Toolbox3 inc SIM,Eng,5 Licence USB Class 100101201: FA-Software: Software PLC
<a href="#">294586</a>	FX5-C1PS-5V FX5UC;Power Supply Unit 5VDC Bus Class 100100111: FA-COM PLC: Other Option
<a href="#">297455</a>	FX5-CNV-IF FX5;FX5UC Bus converter Class 100100111: FA-COM PLC: Other Option
<a href="#">297456</a>	FX5-CNV-BC FX5;Bus Extension cable connector Class 100100111: FA-COM PLC: Other Option
<a href="#">297457</a>	FX5-30EC FX5;Bus Extension cable (0,3m) Class 100100110: FA-COM PLC: Cable
<a href="#">297458</a>	FX5-65EC FX5;Bus Extension cable (0,65m) Class 100100110: FA-COM PLC: Cable
303426	iQ Works V02-15L0C-E iQ Works V2.0,incl Navigator,GX Works,GT Works,MT Works;engl;USB;15 PC's Class 100101201: FA-Software: Software PLC
304614	GX Works3 V01-2L0C-G PLC Programming SW; Melsec iQ-R/iQ- F only (no GXW2/GX Dev); USB; 2 PCs; German Class 100101201: FA-Software: Software PLC
304645	GX Works3 V01-5L0C-G PLC Programming SW; Melsec iQ-R/iQ- F only (no GXW2/GX Dev); USB; 5 PCs; German Class 100101201: FA-Software: Software PLC
308856	GX Works3 V01-2L0C-IT PLC Programming-S/W for Melsec iQ-R/iQ- F;engl;USB;2 PC's; Italian Class 100101201: FA-Software: Software PLC
338821	iQ Works V02-2L0C-G iQ Works V2.0,incl Navigator,GX Works,GT Works,MT Works;German;USB;2 PC's Class 100101201: FA-Software: Software PLC
339022	iQ Works V02-5L0C-G iQ Works V2.0,incl Navigator,GX Works,GT Works,MT Works;German;USB;5 PC's Class 100101201: FA-Software: Software PLC
340984	Transcend SDHC card 16GB Class 10 SDHC memory card 16GB; Class 10; R: 30MB/s; W: 15MB/s Class 100100304: FA-HMI: Other Option
401853	iQ Works V02-2L0C-IT iQ Works V2.0,incl Navigator,GX Works,GT Works,MT Works;Italian;USB;2 PCs Class 100101201: FA-Software: Software PLC
491761	Verbatim microSDHC Card 16GB Class 10 MicroSDHC memory card 16GB; Class 10; R/W: 10MB/s; adapter included Class 100100215: FA-MOD PLC: Other Option

Material	Description / Price List Text / Classification
<a href="#">506255</a>	TRIO-PS-2G/3AC/24DC/40 Primary switched power supply; input: 3-phase, output: 24 VDC/40A, DIN rail Class 100100304: FA-HMI: Other Option
<a href="#">612154</a>	FX5-CNV-BUS-BS FX5;FX3 Bus Conversion Unit; coated Class 100100111: FA-COM PLC: Other Option
<a href="#">612156</a>	FX5-CNV-IFC-BS FX5UC;FX5U Bus Converter; coated Class 100100111: FA-COM PLC: Other Option
<a href="#">612268</a>	Transcend SDHC Card 8GB Class 4 SDHC memory card 8GB; Class 4; R: 18MB/s; W: 6MB/s Class 100100304: FA-HMI: Other Option
<a href="#">697551</a>	IE-C6A-0.2m CC-Link IE Certified Patch Cable RJ45 Cat.6A, 0.2m, for Cabinet Class 100100214: FA-MOD PLC: Cable
<a href="#">697582</a>	IE-C6A-0.5m CC-Link IE Certified Patch Cable RJ45 Cat.6A, 0.5m, for Cabinet Class 100100214: FA-MOD PLC: Cable
<a href="#">697583</a>	IE-C6A-1.0m CC-Link IE Certified Patch Cable RJ45 Cat.6A, 1.0m, for Cabinet Class 100100214: FA-MOD PLC: Cable
<a href="#">697584</a>	IE-C6A-2.0m CC-Link IE Certified Patch Cable RJ45 Cat.6A, 2.0m, for Cabinet Class 100100214: FA-MOD PLC: Cable
<a href="#">697585</a>	IE-C6A-5.0m CC-Link IE Certified Patch Cable RJ45 Cat.6A, 5.0m, for Cabinet Class 100100214: FA-MOD PLC: Cable
<a href="#">697586</a>	IE-C6A-10.0m CC-Link IE Certified Patch Cable RJ45 Cat.6A, 10.0m, for Cabinet Class 100100214: FA-MOD PLC: Cable
<a href="#">697587</a>	IE-C6A-15.0m CC-Link IE Certified Patch Cable RJ45 Cat.6A, 15.0m, for Cabinet Class 100100214: FA-MOD PLC: Cable
<a href="#">697588</a>	IE-C6A-20.0m CC-Link IE Certified Patch Cable RJ45 Cat.6A, 20.0m, for Cabinet Class 100100214: FA-MOD PLC: Cable
<a href="#">697589</a>	IE-C6A-25.0m CC-Link IE Certified Patch Cable RJ45 Cat.6A, 25.0m, for Cabinet Class 100100214: FA-MOD PLC: Cable
<a href="#">697590</a>	IE-CB-1piece CC-Link Bending tool for Patch Cable, RJ45, 1 piece, 90°Deg radius Class 100100215: FA-MOD PLC: Other Option
<a href="#">697591</a>	IE-C6A-CON-1pc CC-Link IE Certified Patch Cable connector, easy clip, RJ45, Cat.6A, 1pc Class 100100215: FA-MOD PLC: Other Option
<a href="#">717285</a>	EDS-G2008-EL 8Port Entry-level Unmanaged Switch,10/100/1000BaseT(X),CCLink IE Field/TSN Cl. A Class 100100211: FA-MOD PLC: Network Module
<a href="#">717286</a>	EDS-G2005-EL 5Port Entry-level Unmanaged Switch,10/100/1000BaseT(X),CCLink IE Field/TSN Cl. A Class 100100211: FA-MOD PLC: Network Module
<a href="#">737856</a>	STEP3-PS/1AC/24DC/2.5/PT Power Supply; input: 1-phase 100-230VAC; output: 22-27VDC/2.5A; push-in Class 100100202: FA-MOD PLC: Power Supply Module
<a href="#">737857</a>	TRIO3-PS/1AC/24DC/5 Power Supply; input: 1-phase 100-230VAC; output: 24-28VDC/5A; push-in Class 100100202: FA-MOD PLC: Power Supply Module
<a href="#">737858</a>	TRIO3-PS/1AC/24DC/10 Power Supply; input: 1-phase 100-230VAC; output: 24-28VDC/10A; push-in Class 100100202: FA-MOD PLC: Power Supply Module
<a href="#">737859</a>	TRIO3-PS/1AC/24DC/20 Power Supply; input: 1-phase 100-230VAC; output: 24-28VDC/20A; push-in Class 100100202: FA-MOD PLC: Power Supply Module
<a href="#">737860</a>	TRIO3-PS/3AC/24DC/20 Power Supply; input: 3-phase 400-500VAC; output: 24-28VDC/20A; push-in Class 100100202: FA-MOD PLC: Power Supply Module