



# MATERIAL FACT SHEET

## 269915 FX3GE-40MT/ES

### General Data

|                     |                                        |
|---------------------|----------------------------------------|
| Product Hierarchy   | IAD214                                 |
|                     | Compact PLC                            |
|                     | FX3G                                   |
| Ext. Material Group | 10 EOL ANNOUNCED                       |
| ABC Indicator       | C (Non-Stock Material / Make-to-Order) |

e-shop: [https://mitsubishi-electric-eshop.mee.com/mee/FA\\_IA/EUR/en/p/000000000000269915](https://mitsubishi-electric-eshop.mee.com/mee/FA_IA/EUR/en/p/000000000000269915)

### FA-COM PLC: Main Unit

|                               |                 |
|-------------------------------|-----------------|
| Series                        | MELSEC-F SERIES |
| Type                          | FX3GE           |
| Power Supply (V)              | 100-240         |
| Current Type                  | AC              |
| Program Memory                | 32K STEPS       |
| Program Memory Unit           | EEPROM          |
| Integrated Digital Inputs     | 24              |
| Integrated Digital Outputs    | 16              |
| Integrated Analogue Inputs    | 2               |
| Output Type                   | TRANSISTOR      |
| Output Logic                  | SINK            |
| Local I/O Points              | 128             |
| Local + Remote I/O Points     | 256             |
| Expandable                    | YES             |
| Cycle Time LD (ns)            | 210             |
| Cycle Time MOV (ns)           | 500             |
| USB                           | 1               |
| Ethernet Port                 | 1               |
| RS-422                        | 1               |
| Power Consumption (W)         | 37              |
| Buffer Battery                | OPTION          |
| Protection Class              | IP10            |
| Min. Ambient Temperature (°C) | 0               |
| Max. Ambient Temperature (°C) | 55              |

### Product Dimensions & Weight

|             |     |
|-------------|-----|
| Width (mm)  | 175 |
| Height (mm) | 90  |
| Depth (mm)  | 86  |
| Weight (kg) | 0,6 |

### Logistic Dimensions & Gross Weight

|                   |       |
|-------------------|-------|
| Length (cm)       | 20,0  |
| Width (cm)        | 12,0  |
| Height (cm)       | 11,5  |
| Gross Weight (kg) | 0,880 |
| Volume (cdm)      | 2,760 |

### Stock Data

|                              |    |
|------------------------------|----|
| Planned Delivery Time (Days) | 72 |
|------------------------------|----|

### Life Cycle

|                          |            |
|--------------------------|------------|
| Sales Start              | 03.12.2013 |
| Discontinued (EOL)       | 26.04.2024 |
| Last Time Buy (LTB)      | 30.05.2025 |
| Last Time Purchase (LTP) | 30.06.2025 |
| End of Service (EOS)     | 30.09.2032 |

|             |                        |
|-------------|------------------------|
| Predecessor | No Predecessor         |
| Successor   | 492976 / FX5UJ-40MT/ES |

### Additional Product Information

|                            |                             |
|----------------------------|-----------------------------|
| Binding Tariff Information | DEBTI-10854/21-1            |
| BTI validity date          | 10.10.2024                  |
| Battery included           | YES - CHECK SPARE PART LIST |

### Export Data

|                                          |            |
|------------------------------------------|------------|
| Legal Control (Dual Use List)            | Not Listed |
| Country of Origin                        | Japan (JP) |
| Preference Status (Supplier Declaration) | Non EU     |

### Environmental

|                            |           |
|----------------------------|-----------|
| REACH Limit Exceeded       | NO        |
| Dangerous Goods Class      | NO        |
| Dangerous Goods Identifier | NO        |
| RoHS Compliance            | COMPLIANT |
| WEEE                       | B2B       |

### Conformity

|        |           |
|--------|-----------|
| CE     | COMPLIANT |
| UL/cUL | COMPLIANT |
| UKCA   | COMPLIANT |

### Documentation & Media Data

|                            |                                                                                                                                                                                                                                                                                               |
|----------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Manual URL Indicator       | <a href="https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=bltdae25c2bd5f2ff94&amp;q=FX3GE-40MT/ES&amp;doc-lang=en">https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=bltdae25c2bd5f2ff94&amp;q=FX3GE-40MT/ES&amp;doc-lang=en</a> |
| Certificates URL Indicator | <a href="https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=blt8050dd1408c11cc2&amp;q=FX3GE-40MT/ES&amp;doc-lang=en">https://emea.mitsubishielectric.com/fa/advanced-search?ct=document&amp;doc-cats=blt8050dd1408c11cc2&amp;q=FX3GE-40MT/ES&amp;doc-lang=en</a> |

### Product Packaging

|                   |       |
|-------------------|-------|
| Cardboard (g)     | 116,5 |
| Other paper (g)   | 0     |
| Aluminum (g)      | 0     |
| Steel (g)         | 0     |
| Styrofoam (g)     | 0     |
| Other plastic (g) | 0     |
| Wood (g)          | 0     |
| Glass (g)         | 0     |
| Others (g)        | 0     |

### Spare parts

| Material               | Description | Quantity | Unit |
|------------------------|-------------|----------|------|
| <a href="#">165286</a> | FX3U-32BL   | 1        | PC   |

### Compatible products

| Material               | Description / Price List Text / Classification                                                                                   |
|------------------------|----------------------------------------------------------------------------------------------------------------------------------|
| <a href="#">31870</a>  | FX-20P-CADP<br>GOT FX Series Adapter cable; 0.3 m<br>Class 100100110: FA-COM PLC: Cable                                          |
| <a href="#">45348</a>  | FX0N-65EC<br>PLC, FX Series Connection Cable for Base and Extension units FX0N/FX2N, 0.65m<br>Class 100100110: FA-COM PLC: Cable |
| <a href="#">70880</a>  | FX2N-CNV-BC<br>PLC, FX2N Adapter for FX extension or special function modules<br>Class 100100111: FA-COM PLC: Other Option       |
| <a href="#">76094</a>  | FX-422CAB0<br>RS422 connection cable for FX0/0S/0N/2N<br>Class 100100110: FA-COM PLC: Cable                                      |
| <a href="#">159642</a> | FX-232AWC-H<br>RS-422/RS-232C converter to connect FX PLC and PC<br>Class 100100111: FA-COM PLC: Other Option                    |
| <a href="#">165286</a> | FX3U-32BL<br>PLC, FX3U/C Battery<br>Class 100100112: FA-COM PLC: Spare Part                                                      |
| <a href="#">165286</a> | FX3U-32BL<br>PLC, FX3U/C Battery<br>Class 100101303: FA-OTHERS: Battery                                                          |

| Material               | Description / Price List Text / Classification                                                                                                 |
|------------------------|------------------------------------------------------------------------------------------------------------------------------------------------|
| <a href="#">169507</a> | FX3U-1PSU-5V<br>PLC, FX Series Power supply module for 5V bus<br>Class 100100111: FA-COM PLC: Other Option                                     |
| <a href="#">221252</a> | FX3G-422-BD<br>PLC, FX3G Interface adapter RS422<br>Class 100100107: FA-COM PLC: Serial Com Module                                             |
| <a href="#">221253</a> | FX3G-485-BD<br>PLC, FX3G Interface module RS485, 1:n Multidrop, network expansion until 50 m<br>Class 100100107: FA-COM PLC: Serial Com Module |
| <a href="#">221254</a> | FX3G-232-BD<br>PLC, FX3G Interface module RS232C<br>Class 100100107: FA-COM PLC: Serial Com Module                                             |
| <a href="#">221265</a> | FX3G-2AD-BD<br>PLC, FX3G Analog adapter, 2 analog inputs, 12bit<br>Class 100100103: FA-COM PLC: Analogue I/O Module                            |
| <a href="#">221266</a> | FX3G-1DA-BD<br>PLC, FX3G Analog adapter, 1 analog output, 12bit<br>Class 100100103: FA-COM PLC: Analogue I/O Module                            |
| <a href="#">221267</a> | FX3G-8AV-BD<br>PLC, FX3G Analog setpoint adapter for 8 setpoint values<br>Class 100100111: FA-COM PLC: Other Option                            |
| <a href="#">221269</a> | FX3G-EEPROM-32L<br>PLC, FX3G EEPROM memory cassette/loader; 32k steps PLC program<br>Class 100100111: FA-COM PLC: Other Option                 |
| <a href="#">221270</a> | FX3G-5DM<br>PLC, FX3G Display Unit<br>Class 100100111: FA-COM PLC: Other Option                                                                |
| <a href="#">221271</a> | FX-30P<br>PLC, FX Series Hand-held programming unit<br>Class 100100111: FA-COM PLC: Other Option                                               |
| <a href="#">221540</a> | USB-CAB-5M<br>USB 2.0 connection cable, plug USB A to plug USB B (mini), 5m<br>Class 100100303: FA-HMI: Cable                                  |
| <a href="#">234630</a> | GX Works2 V01-2L0C-E<br>PLC Programming –S/W for MELSEC Q/L/F; USB; 2 PCs<br>Class 100101201: FA-Software: Software PLC                        |
| <a href="#">234631</a> | GX Works2 V01-5L0C-E<br>PLC Programming –S/W for MELSEC Q/L/F;engl;USB;5 PC's<br>Class 100101201: FA-Software: Software PLC                    |
| <a href="#">244876</a> | GX Works2 V01-2L0C-G<br>PLC Programming –S/W for MELSEC Q/L/F Series; German; USB; 2 PCs<br>Class 100101201: FA-Software: Software PLC         |
| <a href="#">244877</a> | GX Works2 V01-5L0C-G<br>PLC Programming –S/W for MELSEC Q/L/F; USB; 5 PCs<br>Class 100101201: FA-Software: Software PLC                        |
| <a href="#">248245</a> | FX-20P-CAB0<br>PLC, FX Series Connection Cable with FX-10P-E/FX-20P-ESET0/FX-10DM-E,1,5m<br>Class 100100110: FA-COM PLC: Cable                 |
| <a href="#">271699</a> | FX3G-485-BD-RJ<br>FX3G RS485 BD Board;RJ45 Connector Type<br>Class 100100107: FA-COM PLC: Serial Com Module                                    |
| <a href="#">271700</a> | FX3G-4EX-BD<br>FX3G BD Board 4 Inputs DC24V<br>Class 100100102: FA-COM PLC: Digital I/O Module                                                 |
| <a href="#">271701</a> | FX3G-2EYT-BD<br>FX3G BD Board 2 Transistor Outputs<br>Class 100100102: FA-COM PLC: Digital I/O Module                                          |
| <a href="#">278166</a> | SC-E5EW-S45M<br>Ethernet cable; CC-Link IE; category 5e; dbl. shielded/STP; straight; indoor;45m<br>Class 100100214: FA-MOD PLC: Cable         |
| <a href="#">285598</a> | FX0N-30EC<br>PLC, FX Series Connection Cable for Base and Extension units FX0N/FX2N, 0.30m<br>Class 100100110: FA-COM PLC: Cable               |
| <a href="#">286227</a> | iQ Works V02-2L0C-E<br>iQ Works V2.0;incl Navigator,GX Works,GT Works,MT Works;engl;USB;2 PC's<br>Class 100101201: FA-Software: Software PLC   |
| <a href="#">286228</a> | iQ Works V02-5L0C-E<br>iQ Works V2.0;incl Navigator,GX Works,GT Works,MT Works;engl;USB;5 PC's<br>Class 100101201: FA-Software: Software PLC   |

| Material               | Description / Price List Text / Classification                                                                                                  |
|------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------|
| 291807                 | SC-E5EW-S1M-MV<br>Ethernet cable; CC-Link IE; category 5e; dbl. shielded/STP; straight; indoor; 1m<br>Class 100100214: FA-MOD PLC: Cable        |
| 291808                 | SC-E5EW-S3M-MV<br>Ethernet cable; CC-Link IE; category 5e; dbl. shielded/STP; straight; indoor; 3m<br>Class 100100214: FA-MOD PLC: Cable        |
| <a href="#">295425</a> | SC-E5EW-S05M<br>Ethernet cable; CC-Link IE; category 5e; dbl. shielded/STP; straight;indoor;0.5m<br>Class 100100214: FA-MOD PLC: Cable          |
| <a href="#">295426</a> | SC-E5EW-S1M<br>Ethernet cable; CC-Link IE; category 5e; dbl. shielded/STP; straight; indoor; 1m<br>Class 100100214: FA-MOD PLC: Cable           |
| <a href="#">295427</a> | SC-E5EW-S3M<br>Ethernet cable; CC-Link IE; category 5e; dbl. shielded/STP; straight; indoor; 2m<br>Class 100100214: FA-MOD PLC: Cable           |
| <a href="#">303426</a> | iQ Works V02-15L0C-E<br>iQ Works V2.0;incl Navigator,GX Works,GT Works,MT Works;engl;USB;15 PC´s<br>Class 100101201: FA-Software: Software PLC  |
| <a href="#">338821</a> | iQ Works V02-2L0C-G<br>iQ Works V2.0;incl Navigator,GX Works,GT Works,MT Works;German;USB;2 PC´s<br>Class 100101201: FA-Software: Software PLC  |
| <a href="#">339022</a> | iQ Works V02-5L0C-G<br>iQ Works V2.0;incl Navigator,GX Works,GT Works,MT Works;German;USB;5 PC´s<br>Class 100101201: FA-Software: Software PLC  |
| <a href="#">401853</a> | iQ Works V02-2L0C-IT<br>iQ Works V2.0;incl Navigator,GX Works,GT Works,MT Works;Italian;USB;2 PCs<br>Class 100101201: FA-Software: Software PLC |
| <a href="#">413182</a> | SC-E5EW-S10M<br>Ethernet cable; CC-Link IE; category 5e; dbl. shielded/STP; straight; indoor;10m<br>Class 100100214: FA-MOD PLC: Cable          |
| <a href="#">413183</a> | SC-E5EW-S25M<br>Ethernet cable; CC-Link IE; category 5e; dbl. shielded/STP; straight; indoor;25m<br>Class 100100214: FA-MOD PLC: Cable          |
| <a href="#">413184</a> | SC-E5EW-S5M<br>Ethernet cable; CC-Link IE; category 5e; dbl. shielded/STP; straight; indoor; 5m<br>Class 100100214: FA-MOD PLC: Cable           |
| <a href="#">486376</a> | SC-E5EW-S2M<br>Ethernet cable; CC-Link IE; category 5e; dbl. shielded/STP; straight; indoor; 2m<br>Class 100100214: FA-MOD PLC: Cable           |
| <a href="#">486377</a> | SC-E5EW-S4M<br>Ethernet cable; CC-Link IE; category 5e; dbl. shielded/STP; straight; indoor; 4m<br>Class 100100214: FA-MOD PLC: Cable           |
| <a href="#">487403</a> | SC-E5EW-S15M<br>Ethernet cable; CC-Link IE; category 5e; dbl. shielded/STP; straight; indoor;15m<br>Class 100100214: FA-MOD PLC: Cable          |
| <a href="#">487404</a> | SC-E5EW-S20M<br>Ethernet cable; CC-Link IE; category 5e; dbl. shielded/STP; straight; indoor;20m<br>Class 100100214: FA-MOD PLC: Cable          |
| <a href="#">557483</a> | SC-E5EW-S100M<br>Ethernet cable; CC-Link IE; category 5e; dbl. shielded/STP; straight;indoor;100m<br>Class 100100214: FA-MOD PLC: Cable         |